## **SIEMENS**

Data sheet 3RP2505-2BT20



Timing relay, Multifunction 2 change-over contacts, 27 functions 7 time ranges (0.05 s...100 h) 400-440 V AC at 50/60 Hz AC with LED Spring-type terminal (push-in)

product brand name	SIRIUS
product designation	timing relay
design of the product	27 functions
product type designation	3RP25
General technical data	
product component	
<ul> <li>relay output</li> </ul>	Yes
semi-conductor output	No
product extension required remote control	No
product extension optional remote control	No
power loss [W] maximum	2 W
insulation voltage for overvoltage category III according to IEC 60664 with degree of pollution 3 rated value	500 V
test voltage for isolation test	2.5 kV
degree of pollution	3
surge voltage resistance rated value	4 000 V
protection class IP	IP20
shock resistance acc. to IEC 60068-2-27	11g / 15 ms
vibration resistance acc. to IEC 60068-2-6	10 55 Hz / 0.35 mm
mechanical service life (switching cycles) typical	10 000 000
electrical endurance (switching cycles) at AC-15 at 230 V typical	100 000
adjustable time	0.05 s 100 h
relative setting accuracy relating to full-scale value	5 %
thermal current	5 A
minimum ON period	35 ms
recovery time	150 ms
reference code acc. to IEC 81346-2	K
relative repeat accuracy	1 %
Substance Prohibitance (Date)	12.09.2014 00:00:00
Control circuit/ Control	
type of voltage of the control supply voltage	AC
control supply voltage 1 at AC	
● at 50 Hz	400 440 V
● at 60 Hz	400 440 V
control supply voltage frequency 1	50 60 Hz
operating range factor control supply voltage rated value at AC at 50 Hz	
initial value	0.85
• full-scale value	1.1

operating range factor control supply voltage rated value at AC at 60 Hz	
initial value	0.85
full-scale value	1.1
inrush current peak	
• at 440 V	1.5 A
duration of inrush current peak	
• at 440 V	0.1 ms
Switching Function	
switching function	
ON-delay	Yes
<ul> <li>ON-delay/instantaneous contact</li> </ul>	Yes
<ul> <li>passing make contact</li> </ul>	Yes
<ul> <li>passing make contact/instantaneous contact</li> </ul>	Yes
OFF delay	No
switching function	
<ul> <li>flashing symmetrically with interval start/instantaneous</li> </ul>	Yes
flashing symmetrically with interval start	Yes
flashing symmetrically with pulse	Yes
start/instantaneous	
<ul> <li>flashing symmetrically with pulse start</li> </ul>	Yes
<ul> <li>flashing asymmetrically with interval start</li> </ul>	No
flashing asymmetrically with pulse start	No
switching function	
star-delta circuit with delay time	No
star-delta circuit	Yes
switching function with control signal	V
additive ON-delay     pageing break contact	Yes
<ul><li>passing break contact</li><li>passing break contact/instantaneous</li></ul>	Yes Yes
OFF delay	Yes
OFF delay/instantaneous	Yes
pulse delayed	Yes
<ul> <li>pulse delayed/instantaneous</li> </ul>	Yes
• pulse-shaping	Yes
<ul><li>pulse-shaping/instantaneous</li></ul>	Yes
additive ON-delay/instantaneous	Yes
ON-delay/OFF-delay/instantaneous	Yes
passing make contact	Yes
passing make contact/instantaneous contact	Yes
switching function of interval relay with control signal	
<ul> <li>retrotriggerable with deactivated control signal/instantaneous contact</li> </ul>	Yes
<ul> <li>retrotriggerable with switched-on control signal</li> </ul>	Yes
<ul> <li>retrotriggerable with switched-on control signal/instantaneous contact</li> </ul>	Yes
retriggerable with deactivated control signal	Yes
design of the control terminal non-floating	Yes
Short-circuit protection	fund all (aC): A A
design of the fuse link for short-circuit protection of the auxiliary switch required	fuse gL/gG: 4 A
Auxiliary circuit	1.0.00
material of switching contacts	AgSnO2
number of NC contacts delayed switching	0
number of NO contacts delayed switching	0
number of CO contacts delayed switching	2
operational current of auxiliary contacts at AC-15  • at 24 V	3 A
• at 24 V	3 A
• at 250 V	3 A
₩ at 700 v	U.A.

·	
operational current of auxiliary contacts at DC-13	
• at 24 V	1 A
• at 125 V	0.2 A
• at 250 V	0.1 A
operating frequency with 3RT2 contactor maximum	5 000 1/h
contact reliability of auxiliary contacts	one incorrect switching operation of 100 million switching operations (17 V, 5 mA)
contact rating of auxiliary contacts according to UL	R300 / B300
influence of the surrounding temperature	1% in the whole temperature range to the set runtime
power supply influence	1% in the whole voltage range to the set runtime
switching capacity current with inductive load	0.01 3 A
Inputs/ Outputs	
<ul> <li>product function</li> <li>at the relay outputs switchover delayed/without delay</li> </ul>	Yes
non-volatile	No
Electromagnetic compatibility	
EMC emitted interference acc. to IEC 61812-1	ambience A (industrial sector)
EMC immunity acc. to IEC 61812-1	corresponds to degree of severity 3
conducted interference	, , , , , , , , , , , , , , , , , , , ,
due to burst acc. to IEC 61000-4-4	2 kV network connection / 1 kV control connection
• due to conductor-earth surge acc. to IEC 61000-4-5	2 kV
due to conductor-conductor surge acc. to IEC 61000-4-5	1 kV
field-based interference acc. to IEC 61000-4-3	10 V/m
electrostatic discharge acc. to IEC 61000-4-2	4 kV contact discharge / 8 kV air discharge
Safety related data	
protection class IP on the front acc. to IEC 60529	IP20
type of insulation	Basic insulation
category acc. to EN 954-1	none
Connections/ Terminals	
product component removable terminal for auxiliary and control circuit	Yes
type of electrical connection for auxiliary and control circuit	spring-loaded terminals (push-in)
type of connectable conductor cross-sections	
• solid	0.5 4 mm²
• finely stranded with core end processing	0.5 2.5 mm²
<ul><li>finely stranded with core end processing</li><li>finely stranded without core end processing</li></ul>	0.5 2.5 mm <sup>2</sup> 0.5 4 mm <sup>2</sup>
<ul> <li>finely stranded with core end processing</li> <li>finely stranded without core end processing</li> <li>at AWG cables solid</li> </ul>	0.5 2.5 mm <sup>2</sup> 0.5 4 mm <sup>2</sup> 20 12
<ul> <li>finely stranded with core end processing</li> <li>finely stranded without core end processing</li> <li>at AWG cables solid</li> <li>at AWG cables stranded</li> </ul>	0.5 2.5 mm <sup>2</sup> 0.5 4 mm <sup>2</sup>
<ul> <li>finely stranded with core end processing</li> <li>finely stranded without core end processing</li> <li>at AWG cables solid</li> <li>at AWG cables stranded</li> </ul> connectable conductor cross-section	0.5 2.5 mm <sup>2</sup> 0.5 4 mm <sup>2</sup> 20 12 20 12
<ul> <li>finely stranded with core end processing</li> <li>finely stranded without core end processing</li> <li>at AWG cables solid</li> <li>at AWG cables stranded</li> <li>connectable conductor cross-section</li> <li>solid</li> </ul>	0.5 2.5 mm <sup>2</sup> 0.5 4 mm <sup>2</sup> 20 12 20 12 0.5 4 mm <sup>2</sup>
<ul> <li>finely stranded with core end processing</li> <li>finely stranded without core end processing</li> <li>at AWG cables solid</li> <li>at AWG cables stranded</li> </ul> connectable conductor cross-section <ul> <li>solid</li> <li>finely stranded with core end processing</li> </ul>	0.5 2.5 mm <sup>2</sup> 0.5 4 mm <sup>2</sup> 20 12 20 12 0.5 4 mm <sup>2</sup> 0.5 2.5 mm <sup>2</sup>
finely stranded with core end processing     finely stranded without core end processing     at AWG cables solid     at AWG cables stranded     connectable conductor cross-section     solid     finely stranded with core end processing     finely stranded without core end processing  AWG number as coded connectable conductor cross	0.5 2.5 mm <sup>2</sup> 0.5 4 mm <sup>2</sup> 20 12 20 12 0.5 4 mm <sup>2</sup>
finely stranded with core end processing     finely stranded without core end processing     at AWG cables solid     at AWG cables stranded  connectable conductor cross-section     solid     finely stranded with core end processing     finely stranded without core end processing  AWG number as coded connectable conductor cross section	0.5 2.5 mm <sup>2</sup> 0.5 4 mm <sup>2</sup> 20 12 20 12 0.5 4 mm <sup>2</sup> 0.5 2.5 mm <sup>2</sup> 0.5 2.5 mm <sup>2</sup>
finely stranded with core end processing     finely stranded without core end processing     at AWG cables solid     at AWG cables stranded  connectable conductor cross-section     solid     finely stranded with core end processing     finely stranded without core end processing  AWG number as coded connectable conductor cross section     solid	0.5 2.5 mm <sup>2</sup> 0.5 4 mm <sup>2</sup> 20 12 20 12  0.5 4 mm <sup>2</sup> 0.5 2.5 mm <sup>2</sup> 0.5 4 mm <sup>2</sup>
finely stranded with core end processing     finely stranded without core end processing     at AWG cables solid     at AWG cables stranded      connectable conductor cross-section     solid     finely stranded with core end processing     finely stranded without core end processing  AWG number as coded connectable conductor cross section     solid     stranded	0.5 2.5 mm <sup>2</sup> 0.5 4 mm <sup>2</sup> 20 12 20 12 0.5 4 mm <sup>2</sup> 0.5 2.5 mm <sup>2</sup> 0.5 2.5 mm <sup>2</sup>
finely stranded with core end processing     finely stranded without core end processing     at AWG cables solid     at AWG cables stranded     connectable conductor cross-section     solid     finely stranded with core end processing     finely stranded without core end processing  AWG number as coded connectable conductor cross section     solid     stranded  Installation/ mounting/ dimensions	0.5 2.5 mm <sup>2</sup> 0.5 4 mm <sup>2</sup> 20 12 20 12  0.5 4 mm <sup>2</sup> 0.5 2.5 mm <sup>2</sup> 0.5 2.4 mm <sup>2</sup> 20 12
finely stranded with core end processing     finely stranded without core end processing     at AWG cables solid     at AWG cables stranded     connectable conductor cross-section     solid     finely stranded with core end processing     finely stranded without core end processing     AWG number as coded connectable conductor cross section     solid     stranded Installation/ mounting/ dimensions  mounting position	0.5 2.5 mm² 0.5 4 mm² 20 12 20 12  0.5 4 mm² 0.5 2.5 mm² 0.5 4 mm² 20 12  20 12
finely stranded with core end processing     finely stranded without core end processing     at AWG cables solid     at AWG cables stranded  connectable conductor cross-section     solid     finely stranded with core end processing     finely stranded without core end processing  AWG number as coded connectable conductor cross section     solid     stranded  Installation/ mounting/ dimensions  mounting position fastening method	0.5 2.5 mm² 0.5 4 mm² 20 12 20 12  0.5 4 mm² 0.5 2.5 mm² 0.5 2.5 mm² 0.5 4 mm²  any screw and snap-on mounting onto 35 mm standard mounting rail
finely stranded with core end processing     finely stranded without core end processing     at AWG cables solid     at AWG cables stranded  connectable conductor cross-section     solid     finely stranded with core end processing     finely stranded without core end processing  AWG number as coded connectable conductor cross section     solid     stranded  Installation/ mounting/ dimensions  mounting position  fastening method height	0.5 2.5 mm² 0.5 4 mm² 20 12 20 12  0.5 4 mm² 0.5 2.5 mm² 0.5 2.5 mm² 0.5 4 mm²  20 12  20 12
finely stranded with core end processing     finely stranded without core end processing     at AWG cables solid     at AWG cables stranded     connectable conductor cross-section     solid     finely stranded with core end processing     finely stranded without core end processing  AWG number as coded connectable conductor cross section     solid     stranded  Installation/ mounting/ dimensions  mounting position  fastening method  height  width	0.5 2.5 mm² 0.5 4 mm² 20 12 20 12  0.5 4 mm² 0.5 2.5 mm² 0.5 4 mm²  20 12  20 12  20 12  20 12  20 12  20 12  any screw and snap-on mounting onto 35 mm standard mounting rail 100 mm 22.5 mm
finely stranded with core end processing     finely stranded without core end processing     at AWG cables solid     at AWG cables stranded     connectable conductor cross-section     solid     finely stranded with core end processing     finely stranded without core end processing  AWG number as coded connectable conductor cross section     solid     stranded  Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth	0.5 2.5 mm² 0.5 4 mm² 20 12 20 12  0.5 4 mm² 0.5 2.5 mm² 0.5 2.5 mm² 0.5 4 mm²  20 12  20 12
finely stranded with core end processing     finely stranded without core end processing     at AWG cables solid     at AWG cables stranded     connectable conductor cross-section     solid     finely stranded with core end processing     finely stranded without core end processing     AWG number as coded connectable conductor cross section     solid     stranded     Installation/ mounting/ dimensions     mounting position     fastening method     height     width     depth     required spacing	0.5 2.5 mm² 0.5 4 mm² 20 12 20 12  0.5 4 mm² 0.5 2.5 mm² 0.5 4 mm²  20 12  20 12  20 12  20 12  20 12  20 12  2n 12  2n 12  2n 12  2n 12  2n 12
<ul> <li>finely stranded with core end processing</li> <li>finely stranded without core end processing</li> <li>at AWG cables solid</li> <li>at AWG cables stranded</li> <li>connectable conductor cross-section</li> <li>solid</li> <li>finely stranded with core end processing</li> <li>finely stranded without core end processing</li> <li>AWG number as coded connectable conductor cross section</li> <li>solid</li> <li>stranded</li> <li>Installation/ mounting/ dimensions</li> <li>mounting position</li> <li>fastening method</li> <li>height</li> <li>width</li> <li>depth</li> <li>required spacing</li> <li>with side-by-side mounting</li> </ul>	0.5 2.5 mm² 0.5 4 mm² 20 12 20 12  0.5 4 mm² 0.5 2.5 mm² 0.5 4 mm²  20 12  20 12  20 12  20 12  20 12  20 12  90 12
<ul> <li>finely stranded with core end processing</li> <li>finely stranded without core end processing</li> <li>at AWG cables solid</li> <li>at AWG cables stranded</li> <li>connectable conductor cross-section</li> <li>solid</li> <li>finely stranded with core end processing</li> <li>finely stranded without core end processing</li> <li>AWG number as coded connectable conductor cross section</li> <li>solid</li> <li>stranded</li> <li>Installation/ mounting/ dimensions</li> <li>mounting position</li> <li>fastening method</li> <li>height</li> <li>width</li> <li>depth</li> <li>required spacing</li> <li>with side-by-side mounting</li> <li>forwards</li> </ul>	0.5 2.5 mm² 0.5 4 mm² 20 12 20 12  0.5 4 mm² 0.5 2.5 mm² 0.5 4 mm²  20 12  20 12  20 12  20 12  20 12  90 12  any screw and snap-on mounting onto 35 mm standard mounting rail 100 mm 22.5 mm 90 mm
<ul> <li>finely stranded with core end processing</li> <li>finely stranded without core end processing</li> <li>at AWG cables solid</li> <li>at AWG cables stranded</li> <li>connectable conductor cross-section</li> <li>solid</li> <li>finely stranded with core end processing</li> <li>finely stranded without core end processing</li> <li>AWG number as coded connectable conductor cross section</li> <li>solid</li> <li>stranded</li> <li>Installation/ mounting/ dimensions</li> <li>mounting position</li> <li>fastening method</li> <li>height</li> <li>width</li> <li>depth</li> <li>required spacing</li> <li>with side-by-side mounting</li> <li>— forwards</li> <li>— backwards</li> </ul>	0.5 2.5 mm² 0.5 4 mm² 20 12 20 12  0.5 4 mm² 0.5 2.5 mm² 0.5 4 mm²  20 12  20 12  20 12  20 12  20 12  20 12  any screw and snap-on mounting onto 35 mm standard mounting rail 100 mm 22.5 mm 90 mm
<ul> <li>finely stranded with core end processing</li> <li>finely stranded without core end processing</li> <li>at AWG cables solid</li> <li>at AWG cables stranded</li> <li>connectable conductor cross-section</li> <li>solid</li> <li>finely stranded with core end processing</li> <li>finely stranded without core end processing</li> </ul> AWG number as coded connectable conductor cross section <ul> <li>solid</li> <li>stranded</li> </ul> Installation/ mounting/ dimensions mounting position fastening method height <ul> <li>width</li> <li>depth</li> </ul> required spacing <ul> <li>with side-by-side mounting</li> <li>forwards</li> <li>backwards</li> <li>upwards</li> </ul>	0.5 2.5 mm² 0.5 4 mm² 20 12 20 12 0.5 4 mm² 0.5 2.5 mm² 0.5 4 mm²  20 12 20 12 20 12 20 12 20 12  any screw and snap-on mounting onto 35 mm standard mounting rail 100 mm 22.5 mm 90 mm  0 mm 0 mm 0 mm
<ul> <li>finely stranded with core end processing</li> <li>finely stranded without core end processing</li> <li>at AWG cables solid</li> <li>at AWG cables stranded</li> <li>connectable conductor cross-section</li> <li>solid</li> <li>finely stranded with core end processing</li> <li>finely stranded without core end processing</li> <li>AWG number as coded connectable conductor cross section</li> <li>solid</li> <li>stranded</li> <li>Installation/ mounting/ dimensions</li> <li>mounting position</li> <li>fastening method</li> <li>height</li> <li>width</li> <li>depth</li> <li>required spacing</li> <li>with side-by-side mounting</li> <li>— forwards</li> <li>— backwards</li> </ul>	0.5 2.5 mm² 0.5 4 mm² 20 12 20 12  0.5 4 mm² 0.5 2.5 mm² 0.5 4 mm²  20 12  20 12  20 12  20 12  20 12  20 12  any screw and snap-on mounting onto 35 mm standard mounting rail 100 mm 22.5 mm 90 mm

<ul> <li>for grounded parts</li> </ul>	
— forwards	0 mm
— backwards	0 mm
— upwards	0 mm
— at the side	0 mm
<ul><li>downwards</li></ul>	0 mm
for live parts	
— forwards	0 mm
— backwards	0 mm
— upwards	0 mm
<ul><li>downwards</li></ul>	0 mm
— at the side	0 mm
Ambient conditions	
installation altitude at height above sea level maximum	2 000 m
ambient temperature	
<ul> <li>during operation</li> </ul>	-25 +60 °C
<ul> <li>during storage</li> </ul>	-40 +85 °C
during transport	-40 +85 °C
relative humidity during operation	10 95 %
Certificates/ approvals	

**General Product Approval** 

**EMC** 

Declaration of Conformity











**Miscellaneous** 

**Declaration of Conformity** 

**Test Certificates** 

Marine / Shipping



Type Test Certificates/Test Report









Marine / Shipping

other





Confirmation

## Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RP2505-2BT20

Cax online generator

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)


https://support.industry.siemens.com/cs/ww/en/ps/3RP2505-2BT20


Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3RP2505-2BT20&lang=en

**Characteristic: Derating** 

https://support.industry.siemens.com/cs/ww/en/ps/3RP2505-2BT20/manual





last modified: 8/24/2021 🖸