SIEMENS

Data sheet

3RP2555-1AW30



time relay, electronic flasher relay asymmetrical 1 change-over contact 2x7 time ranges, 0.05 s-100 h 12-240 V AC/DC at 50/60 Hz AC with LED, screw terminal

product brand name	SIRIUS		
product designation	timing relay		
design of the product	Clock generator, flashing, asymmetrical		
product type designation	3RP25		
General technical data			
product component			
● relay output	Yes		
 semi-conductor output 	No		
product extension required remote control	No		
product extension optional remote control	No		
power loss [W] maximum	2 W		
insulation voltage for overvoltage category III according to IEC 60664 with degree of pollution 3 rated value	300 V		
test voltage for isolation test	2.5 kV		
degree of pollution	3		
surge voltage resistance rated value	4 000 V		
protection class IP	IP20		
shock resistance acc. to IEC 60068-2-27	11g / 15 ms		
vibration resistance acc. to IEC 60068-2-6	10 55 Hz / 0.35 mm		
mechanical service life (switching cycles) typical	10 000 000		
electrical endurance (switching cycles) at AC-15 at 230 V typical	100 000		
adjustable time	0.05 s 100 h		
relative setting accuracy relating to full-scale value	5 %		
thermal current	5 A		
recovery time	250 ms		
reference code acc. to IEC 81346-2	К		
relative repeat accuracy	1 %		
Substance Prohibitance (Date)	12.09.2014 00:00:00		
Control circuit/ Control			
type of voltage of the control supply voltage	AC/DC		
control supply voltage 1 at AC			
• at 50 Hz	12 240 V		
• at 60 Hz	12 240 V		
control supply voltage frequency 1	50 60 Hz		
control supply voltage 1			
● at DC	12 240 V		
operating range factor control supply voltage rated value at DC			
 initial value 	0.8		

 full-scale value 	1.1
operating range factor control supply voltage rated	
value at AC at 50 Hz	
 initial value 	0.8
full-scale value	1.1
operating range factor control supply voltage rated	
value at AC at 60 Hz	
initial value	0.8
full-scale value	1.1
inrush current peak	
• at 24 V	0.4 A
• at 240 V	5 A
duration of inrush current peak	
• at 24 V	0.4 ms
• at 240 V	0.5 ms
Switching Function	
switching function	
 ON-delay 	No
 ON-delay/instantaneous contact 	No
 passing make contact 	No
 passing make contact/instantaneous contact 	No
OFF delay	No
switching function	
 flashing symmetrically with interval 	No
start/instantaneous	
 flashing symmetrically with interval start 	No
 flashing symmetrically with pulse 	No
start/instantaneous	A la
flashing symmetrically with pulse start	No
 flashing asymmetrically with interval start 	Yes
flashing asymmetrically with pulse start	No
switching function	
star-delta circuit with delay time	No
star-delta circuit	No
switching function with control signal	
additive ON-delay	No
 passing break contact 	No
passing break contact/instantaneous	No
• OFF delay	No
 OFF delay/instantaneous 	No
 pulse delayed 	
	No
pulse delayed/instantaneous	No
 pulse delayed/instantaneous pulse-shaping	No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous	No No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous 	No No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous ON-delay/OFF-delay/instantaneous 	No No No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous ON-delay/OFF-delay/instantaneous passing make contact 	No No No No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous ON-delay/OFF-delay/instantaneous passing make contact passing make contact/instantaneous contact 	No No No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous ON-delay/OFF-delay/instantaneous passing make contact passing make contact/instantaneous contact switching function of interval relay with control signal 	No No No No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous ON-delay/OFF-delay/instantaneous passing make contact passing make contact/instantaneous contact switching function of interval relay with control signal retrotriggerable with deactivated control 	No No No No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous ON-delay/OFF-delay/instantaneous passing make contact passing make contact/instantaneous contact switching function of interval relay with control signal retrotriggerable with deactivated control signal/instantaneous contact 	No No No No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous ON-delay/OFF-delay/instantaneous passing make contact passing make contact/instantaneous contact switching function of interval relay with control signal retrotriggerable with deactivated control signal retrotriggerable with switched-on control signal 	No No No No No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous ON-delay/OFF-delay/instantaneous passing make contact passing make contact/instantaneous contact switching function of interval relay with control signal retrotriggerable with deactivated control signal retrotriggerable with switched-on control signal retrotriggerable with switched-on control 	No No No No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous ON-delay/OFF-delay/instantaneous passing make contact passing make contact/instantaneous contact switching function of interval relay with control signal retrotriggerable with deactivated control signal/instantaneous contact retrotriggerable with switched-on control signal retrotriggerable with switched-on control signal retrotriggerable with switched-on control signal/instantaneous contact 	No No No No No No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous ON-delay/OFF-delay/instantaneous passing make contact passing make contact/instantaneous contact switching function of interval relay with control signal retrotriggerable with deactivated control signal/instantaneous contact retrotriggerable with switched-on control signal 	No No No No No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous ON-delay/OFF-delay/instantaneous passing make contact passing make contact/instantaneous contact switching function of interval relay with control signal retrotriggerable with deactivated control signal retrotriggerable with switched-on control signal retrotriggerable with switched-on control signal retrotriggerable with deactivated control signal 	No No No No No No No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous ON-delay/OFF-delay/instantaneous passing make contact passing make contact/instantaneous contact switching function of interval relay with control signal retrotriggerable with deactivated control signal retrotriggerable with switched-on control signal retrotriggerable with switched-on control signal/instantaneous contact retrotriggerable with switched-on control signal retrotriggerable with deactivated control signal signal/instantaneous contact retriggerable with deactivated control signal design of the fuse link for short-circuit protection of the 	No No No No No No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous ON-delay/OFF-delay/instantaneous passing make contact passing make contact/instantaneous contact switching function of interval relay with control signal retrotriggerable with deactivated control signal retrotriggerable with switched-on control signal retrotriggerable with switched-on control signal retrotriggerable with deactivated control signal retrotriggerable with deactivated control signal retrotriggerable with switched-on control signal retriggerable with deactivated control signal design of the fuse link for short-circuit protection of the auxiliary switch required 	No No No No No No No No
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous ON-delay/OFF-delay/instantaneous passing make contact passing make contact/instantaneous contact switching function of interval relay with control signal retrotriggerable with deactivated control signal retrotriggerable with switched-on control signal retrotriggerable with switched-on control signal retrotriggerable with switched-on control signal retrotriggerable with deactivated control signal retrotriggerable with switched-on control signal signal/instantaneous contact retriggerable with deactivated control signal design of the fuse link for short-circuit protection of the auxiliary switch required 	No No No No No No No Fuse gL/gG: 4 A
 pulse delayed/instantaneous pulse-shaping pulse-shaping/instantaneous additive ON-delay/instantaneous ON-delay/OFF-delay/instantaneous passing make contact passing make contact/instantaneous contact switching function of interval relay with control signal retrotriggerable with deactivated control signal retrotriggerable with switched-on control signal retrotriggerable with switched-on control signal retrotriggerable with deactivated control signal retrotriggerable with deactivated control signal retrotriggerable with switched-on control signal retrotriggerable with deactivated control signal signal/instantaneous contact retriggerable with deactivated control signal 	No No No No No No No

Subject to change without notice © Copyright Siemens

number of NO contacts delayed switching	
number of NO contacts delayed switching	0
number of CO contacts delayed switching	1
operational current of auxiliary contacts at AC-15	
• at 24 V	3 A
• at 250 V	3 A
operational current of auxiliary contacts at DC-13	
• at 24 V	1 A
• at 125 V	0.2 A
● at 250 V	0.1 A
operating frequency with 3RT2 contactor maximum	5 000 1/h
contact reliability of auxiliary contacts	one incorrect switching operation of 100 million switching operations (17
	V, 5 mA)
contact rating of auxiliary contacts according to UL	R300 / B300
influence of the surrounding temperature	1% in the whole temperature range to the set runtime
power supply influence	1% in the whole voltage range to the set runtime
switching capacity current with inductive load	0.01 3 A
Inputs/ Outputs	
product function	
 at the relay outputs switchover delayed/without 	No
delay	
non-volatile	No
Electromagnetic compatibility	
EMC emitted interference acc. to IEC 61812-1	ambience A (industrial sector)
EMC immunity acc. to IEC 61812-1	corresponds to degree of severity 3
conducted interference	
	2 kV network connection / 1 kV control connection
due to burst acc. to IEC 61000-4-4	
• due to conductor-earth surge acc. to IEC 61000-4-5	2 kV
 due to conductor-conductor surge acc. to IEC 61000-4-5 	1 kV
field-based interference acc. to IEC 61000-4-3	10 V/m
electrostatic discharge acc. to IEC 61000-4-2	4 kV contact discharge / 8 kV air discharge
Safety related data	
protection class IP on the front acc. to IEC 60529	IP20
type of insulation	Basic insulation
category acc. to EN 954-1	none
Connections/ Terminals	
product component removable terminal for auxiliary	Yes
product component removable terminal for auxiliary and control circuit	
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit	Yes screw-type terminals
product component removable terminal for auxiliary and control circuittype of electrical connection for auxiliary and control circuittype of connectable conductor cross-sections	screw-type terminals
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid 	screw-type terminals 1x (0.5 4.0 mm²), 2x (0.5 2.5 mm²)
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing 	screw-type terminals 1x (0.5 4.0 mm²), 2x (0.5 2.5 mm²) 1x (0.5 4 mm²), 2x (0.5 1.5 mm²)
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid 	screw-type terminals 1x (0.5 4.0 mm ²), 2x (0.5 2.5 mm ²) 1x (0.5 4 mm ²), 2x (0.5 1.5 mm ²) 1x (20 12), 2x (20 14)
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing 	screw-type terminals 1x (0.5 4.0 mm²), 2x (0.5 2.5 mm²) 1x (0.5 4 mm²), 2x (0.5 1.5 mm²)
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid 	screw-type terminals 1x (0.5 4.0 mm ²), 2x (0.5 2.5 mm ²) 1x (0.5 4 mm ²), 2x (0.5 1.5 mm ²) 1x (20 12), 2x (20 14) 1x (20 12), 2x (20 14)
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid at AWG cables stranded 	screw-type terminals 1x (0.5 4.0 mm ²), 2x (0.5 2.5 mm ²) 1x (0.5 4 mm ²), 2x (0.5 1.5 mm ²) 1x (20 12), 2x (20 14) 1x (20 12), 2x (20 14) 0.5 4 mm ²
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid at AWG cables stranded connectable conductor cross-sections	screw-type terminals 1x (0.5 4.0 mm ²), 2x (0.5 2.5 mm ²) 1x (0.5 4 mm ²), 2x (0.5 1.5 mm ²) 1x (20 12), 2x (20 14) 1x (20 12), 2x (20 14)
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid at AWG cables stranded connectable conductor cross-section solid at AWG cables stranded 	screw-type terminals 1x (0.5 4.0 mm ²), 2x (0.5 2.5 mm ²) 1x (0.5 4 mm ²), 2x (0.5 1.5 mm ²) 1x (20 12), 2x (20 14) 1x (20 12), 2x (20 14) 0.5 4 mm ²
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid at AWG cables stranded connectable conductor cross-section solid at AWG cables stranded connectable conductor cross-section solid finely stranded with core end processing AWG number as coded connectable conductor cross	screw-type terminals 1x (0.5 4.0 mm ²), 2x (0.5 2.5 mm ²) 1x (0.5 4 mm ²), 2x (0.5 1.5 mm ²) 1x (20 12), 2x (20 14) 1x (20 12), 2x (20 14) 0.5 4 mm ²
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid at AWG cables stranded connectable conductor cross-section • solid • at AWG cables stranded connectable conductor cross-section • solid • finely stranded with core end processing AWG number as coded connectable conductor cross section	screw-type terminals 1x (0.5 4.0 mm ²), 2x (0.5 2.5 mm ²) 1x (0.5 4 mm ²), 2x (0.5 1.5 mm ²) 1x (20 12), 2x (20 14) 1x (20 12), 2x (20 14) 0.5 4 mm ² 0.5 4 mm ²
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid at AWG cables stranded connectable conductor cross-section solid e at AWG cables stranded connectable conductor cross-section solid finely stranded with core end processing AWG number as coded connectable conductor cross section solid solid solid stranded	screw-type terminals 1x (0.5 4.0 mm ²), 2x (0.5 2.5 mm ²) 1x (0.5 4 mm ²), 2x (0.5 1.5 mm ²) 1x (20 12), 2x (20 14) 1x (20 12), 2x (20 14) 0.5 4 mm ² 0.5 4 mm ² 20 12
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid at AWG cables stranded connectable conductor cross-section solid e at AWG cables stranded connectable conductor cross-section solid finely stranded with core end processing AWG number as coded connectable conductor cross section solid stranded e stranded tightening torque	screw-type terminals 1x (0.5 4.0 mm ²), 2x (0.5 2.5 mm ²) 1x (0.5 4 mm ²), 2x (0.5 1.5 mm ²) 1x (20 12), 2x (20 14) 1x (20 12), 2x (20 14) 0.5 4 mm ² 0.5 4 mm ² 20 12 20 12
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid at AWG cables stranded connectable conductor cross-section solid at AWG cables stranded connectable conductor cross-section solid finely stranded with core end processing AWG number as coded connectable conductor cross section solid stranded tightening torque design of the thread of the connection screw	screw-type terminals 1x ($0.5 \dots 4.0 \text{ mm}^2$), 2x ($0.5 \dots 2.5 \text{ mm}^2$) 1x ($0.5 \dots 4 \text{ mm}^2$), 2x ($0.5 \dots 1.5 \text{ mm}^2$) 1x ($20 \dots 12$), 2x ($20 \dots 14$) 1x ($20 \dots 12$), 2x ($20 \dots 14$) 0.5 4 mm ² 0.5 4 mm ² 20 12 20 12 20 14 0.6 0.8 N·m
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid at AWG cables stranded connectable conductor cross-section solid e at AWG cables stranded connectable conductor cross-section solid finely stranded with core end processing AWG number as coded connectable conductor cross section solid solid stranded tightening torque design of the thread of the connection screw Installation/ mounting/ dimensions	screw-type terminals 1x (0.5 4.0 mm ²), 2x (0.5 2.5 mm ²) 1x (0.5 4 mm ²), 2x (0.5 1.5 mm ²) 1x (20 12), 2x (20 14) 1x (20 12), 2x (20 14) 0.5 4 mm ² 0.5 4 mm ² 20 12 20 12 20 14 0.6 0.8 N·m M3
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid at AWG cables stranded connectable conductor cross-section solid e at AWG cables stranded connectable conductor cross-section solid finely stranded with core end processing AWG number as coded connectable conductor cross section solid sitanded solid stranded utightening torque design of the thread of the connection screw Installation/ mounting/ dimensions mounting position	screw-type terminals 1x (0.5 4.0 mm ²), 2x (0.5 2.5 mm ²) 1x (0.5 4 mm ²), 2x (0.5 1.5 mm ²) 1x (20 12), 2x (20 14) 1x (20 12), 2x (20 14) 0.5 4 mm ² 0.5 4 mm ² 20 12 20 12 20 14 0.6 0.8 N·m M3
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid at AWG cables stranded connectable conductor cross-section solid e at AWG cables stranded connectable conductor cross-section solid finely stranded with core end processing AWG number as coded connectable conductor cross section solid stranded e stranded tightening torque design of the thread of the connection screw Installation/ mounting/ dimensions mounting position fastening method	screw-type terminals $1x (0.5 4.0 \text{ mm}^2), 2x (0.5 2.5 \text{ mm}^2)$ $1x (0.5 4 \text{ mm}^2), 2x (0.5 1.5 \text{ mm}^2)$ 1x (20 12), 2x (20 14) 1x (20 12), 2x (20 14) $0.5 4 \text{ mm}^2$ $0.5 4 \text{ mm}^2$ 20 12 20 12 20 14 0.6 0.8 N·m M3 any screw and snap-on mounting onto 35 mm standard mounting rail
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid at AWG cables stranded connectable conductor cross-section solid at AWG cables solid at AWG cables stranded connectable conductor cross-section solid solid finely stranded with core end processing AWG number as coded connectable conductor cross section solid stranded tightening torque design of the thread of the connection screw Installation/ mounting/ dimensions mounting position fastening method height	screw-type terminals 1x (0.5 4.0 mm ²), 2x (0.5 2.5 mm ²) 1x (0.5 4 mm ²), 2x (0.5 1.5 mm ²) 1x (20 12), 2x (20 14) 1x (20 12), 2x (20 14) 0.5 4 mm ² 0.5 4 mm ² 20 12 20 12 20 14 0.6 0.8 N·m M3 any screw and snap-on mounting onto 35 mm standard mounting rail 100 mm
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid at AWG cables stranded connectable conductor cross-section at AWG cables stranded connectable conductor cross-section solid at AWG cables stranded connectable conductor cross-section solid finely stranded with core end processing AWG number as coded connectable conductor cross section solid solid stranded tightening torque design of the thread of the connection screw Installation/ mounting/ dimensions mounting position fastening method <ld>height width width ittick ittick ittick</ld>	screw-type terminals 1x (0.5 4.0 mm ²), 2x (0.5 2.5 mm ²) 1x (0.5 4 mm ²), 2x (0.5 1.5 mm ²) 1x (20 12), 2x (20 14) 1x (20 12), 2x (20 14) 0.5 4 mm ² 0.5 4 mm ² 20 12 20 14 0.6 0.8 N·m M3 any screw and snap-on mounting onto 35 mm standard mounting rail 100 mm 17.5 mm
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid at AWG cables stranded connectable conductor cross-section solid at AWG cables stranded connectable conductor cross-section solid finely stranded with core end processing AWG number as coded connectable conductor cross section solid stranded tightening torque design of the thread of the connection screw Installation/ mounting/ dimensions mounting position fastening method height width depth 	screw-type terminals 1x (0.5 4.0 mm ²), 2x (0.5 2.5 mm ²) 1x (0.5 4 mm ²), 2x (0.5 1.5 mm ²) 1x (20 12), 2x (20 14) 1x (20 12), 2x (20 14) 0.5 4 mm ² 0.5 4 mm ² 20 12 20 12 20 14 0.6 0.8 N·m M3 any screw and snap-on mounting onto 35 mm standard mounting rail 100 mm
product component removable terminal for auxiliary and control circuit type of electrical connection for auxiliary and control circuit type of connectable conductor cross-sections solid finely stranded with core end processing at AWG cables solid at AWG cables stranded connectable conductor cross-section at AWG cables stranded connectable conductor cross-section solid at AWG cables stranded connectable conductor cross-section solid finely stranded with core end processing AWG number as coded connectable conductor cross section solid solid stranded tightening torque design of the thread of the connection screw Installation/ mounting/ dimensions mounting position fastening method <ld>height width width ittick ittick ittick</ld>	screw-type terminals 1x (0.5 4.0 mm ²), 2x (0.5 2.5 mm ²) 1x (0.5 4 mm ²), 2x (0.5 1.5 mm ²) 1x (20 12), 2x (20 14) 1x (20 12), 2x (20 14) 0.5 4 mm ² 0.5 4 mm ² 20 12 20 14 0.6 0.8 N·m M3 any screw and snap-on mounting onto 35 mm standard mounting rail 100 mm 17.5 mm

— forwards			0 mm		
— backwards	S		0 mm		
— upwards			0 mm		
- downward	ls		0 mm		
— at the side	9		0 mm		
 for grounded particular 	arts				
— forwards			0 mm		
- backwards	S		0 mm		
— upwards			0 mm		
— at the side			0 mm		
- downward	ls		0 mm		
 for live parts 					
— forwards			0 mm		
— backwards	S		0 mm		
— upwards			0 mm		
- downward	ls		0 mm		
— at the side	9		0 mm		
Ambient conditions					
installation altitude at	height above sea level	maximum	2 000 m		
ambient temperatur					
 during operatio 			-25 +60 °C		
during storage			-40 +85 °C		
 during transpor 	t		-40 +85 °C		
relative humidity durin			10 95 %		
Certificates/ approval					
					Declaration of
General Product Ap	oproval			EMC	Conformity
A				A	
(SP)	(\mathbf{w})	ሠ	FAL	Ŕ	CE
S₽		(U)	EAC	RCM	C E
SP M			EAC	RCM	C E EG-Konf.
(S) M	CCC CCC	(UL) ut	EAC	RCM	CE EG-Konf.
(SP) CEA	CCC	(UL) ut	EAC	RCM	CE EG-Konf.
Declaration of		Marine / Shipp	EAC	RCM	C E EG-Konf.
Declaration of Conformity	Ccc Test Certificates	UL Marine / Shipp	ERC	RCM	C E EG-Konf.
Conformity	Test Certificates	Marine / Shipp	EAC	RCM	CE EG-Konf.
	Test Certificates	Marine / Shipp	ERC Ding	RCM	CE EG-Konf.
Conformity	Test Certificates	Marine / Shipp		RCM	C C EG-Konf.
Conformity	Test Certificates	Marine / Shipp	Ding	RCM	C C EG-Konf.
Conformity	Test Certificates	Marine / Shipp	Lloyd's Register	RCM	C C EG-Konf.
Conformity	Test Certificates	BUREAU	Lloyd's Register	RCM	EG-Konf.
Conformity <u>Miscellaneous</u>	Test Certificates	B U R E A U VERITAS	Lloyd's Register	RCM	EG-Konf.
Conformity	Test Certificates	BUREAU	Lloyd's Register	RCM	EG-Konf.
Conformity <u>Miscellaneous</u>	Test Certificates	BUREAU VERITAS	Llovd's Kegister urs	RCM	EG-Konf.
Conformity <u>Miscellaneous</u>	Test Certificates	B U R E A U VERITAS	Llovd's Kegister urs	RCM	EG-Konf.
Conformity <u>Miscellaneous</u>	Test Certificates	BUREAU VERITAS	Llovd's Kegister urs	RCM	EG-Konf.
Conformity <u>Miscellaneous</u>	Test Certificates <u>Type Test Certificates</u> <u>ates/Test Report</u>	BUREAU VERITAS	Llovd's Kegister urs	RCM	EG-Konf.
Conformity <u>Miscellaneous</u>	Test Certificates <u>Type Test Certificates</u> <u>ates/Test Report</u>	BUREAU VERITAS	Llovd's Kegister urs	RCM	EG-Konf.
Conformity <u>Miscellaneous</u>	Test Certificates <u>Type Test Certificates</u> <u>ates/Test Report</u>	BUREAU VERITAS	Llovd's Kegister urs	RCM	СС EG-Konf.
Conformity <u>Miscellaneous</u> Marine / Shipping	Test Certificates <u>Type Test Certificates</u> <u>ates/Test Report</u>	BUREAU VERITAS	Llovd's Kegister urs	Image: Constraint of the constraint	СС БG-Konf.
Conformity Miscellaneous Marine / Shipping EXERS	Test Certificates Type Test Certific- ates/Test Report	other Confirmation	Liks	Image: Constraint of the constraint	EG-Konf.
Conformity Miscellaneous Marine / Shipping EXERS	Test Certificates Type Test Certificates test Certificates test Certificates test Certificates test Certificates test Certificates test Certificates test Certificates test Certificates test Certificates test Certificates test Certificates test Certificates test Certificates test Certificates tes	other Confirmation	Liks	Image: Constraint of the second se	EG-Konf.

Industry Mall (Online ordering system) https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RP2555-1AW30

Cax online generator


http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RP2555-1AW30


Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RP2555-1AW30

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RP2555-1AW30&lang=en

Characteristic: Derating





last modified:

8/24/2021 🖸