6ES7531-7QF00-0AB0

Data sheet



SIMATIC S7-1500 Analog input module, AI 8xU/I/R/RTD BA, 16 bit resolution, Accuracy 0.5%, 8 channels in groups of 8; Common mode voltage 4 V DC, Diagnostics; Hardware interrupts; Delivery including infeed element, shield bracket and shield terminal: Front connector (screw terminals or push-in) to be ordered separately

General information	
Product type designation	AI 8xU/I/R/RTD BA
HW functional status	FS01
Firmware version	V1.0.0
FW update possible	Yes
Product function	
 I&M data 	Yes; I&M0 to I&M3
Prioritized startup	No
Engineering with	
 STEP 7 TIA Portal configurable/integrated from version 	V15.1 / V16
 STEP 7 configurable/integrated from version 	V5.5 SP3 / -
 PROFIBUS from GSD version/GSD revision 	V1.0 / V5.1
PROFINET from GSD version/GSD revision	V2.3 / -
Operating mode	
 Oversampling 	No
• MSI	Yes
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	No
Power	
Power available from the backplane bus	0.85 W
Power loss	
Power loss, typ.	0.9 W
Analog inputs	
Number of analog inputs	8
 For current measurement 	8
 For voltage measurement 	8
 For resistance/resistance thermometer measurement 	8
permissible input voltage for voltage input (destruction limit), max.	12 V; 12 V continuous, 30 V for max. 1 s
permissible input current for current input (destruction limit), max.	40 mA
Constant measurement current for resistance-type transmitter, typ.	230 370 μΑ
Technical unit for temperature measurement adjustable	Yes; °C/°F/K
Input ranges (rated values), voltages	

- 0 to 15 V	Ne
• 0 to +5 V	No
• 0 to +10 V	No V
• 1 V to 5 V	Yes 10 M Ω
— Input resistance (1 V to 5 V)	
• -1 V to +1 V	Yes
— Input resistance (-1 V to +1 V)	10 ΜΩ
• -10 V to +10 V	Yes
— Input resistance (-10 V to +10 V)	10 ΜΩ
• -2.5 V to +2.5 V	No No
• -25 mV to +25 mV	No No
• -250 mV to +250 mV	No
• -5 V to +5 V	Yes
— Input resistance (-5 V to +5 V)	10 ΜΩ
• -50 mV to +50 mV	Yes
— Input resistance (-50 mV to +50 mV)	10 ΜΩ
• -500 mV to +500 mV	Yes
— Input resistance (-500 mV to +500 mV)	10 ΜΩ
● -80 mV to +80 mV	No
Input ranges (rated values), currents	
• 0 to 10 mA	No
• 0 to 20 mA	Yes
— Input resistance (0 to 20 mA)	25 Ω ; Plus approx. 42 ohms for overvoltage protection by PTC
● -20 mA to +20 mA	Yes
— Input resistance (-20 mA to +20 mA)	$25~\Omega$; Plus approx. 42 ohms for overvoltage protection by PTC
• 4 mA to 20 mA	Yes
— Input resistance (4 mA to 20 mA)	25 Ω; Plus approx. 42 ohms for overvoltage protection by PTC
Input ranges (rated values), thermocouples	
▼ Type B	No
• Type C	No
▼ Type E	No
• Type J	No
• Type K	No
• Type L	No
• Type N	No
• Type R	No
• Type S	No
Type T	No
• Type U	No
Type TXK/TXK(L) to GOST	No
Input ranges (rated values), resistance thermometer	
• Cu 10	No
 Cu 10 according to GOST 	No
• Cu 50	No
 Cu 50 according to GOST 	No
• Cu 100	No
 Cu 100 according to GOST 	No
• Ni 10	No
Ni 10 according to GOST	No
• Ni 100	Yes; Standard/climate
— Input resistance (Ni 100)	10 ΜΩ
Ni 100 according to GOST	No
• Ni 1000	Yes; Standard/climate
— Input resistance (Ni 1000)	10 ΜΩ
Ni 1000 according to GOST	No
• LG-Ni 1000	Yes; Standard/climate
— Input resistance (LG-Ni 1000)	10 ΜΩ
• Ni 120	No
Ni 120 according to GOST	No
3333.4	

• Ni 200	No
 Ni 200 according to GOST 	No
• Ni 500	No
 Ni 500 according to GOST 	No
• Pt 10	No
 Pt 10 according to GOST 	No
• Pt 50	No
 Pt 50 according to GOST 	No
• Pt 100	Yes; Standard/climate
— Input resistance (Pt 100)	10 ΜΩ
Pt 100 according to GOST	No
• Pt 1000	Yes; Standard/climate
— Input resistance (Pt 1000)	10 MΩ
Pt 1000 according to GOST	No
• Pt 200	No
Pt 200 according to GOST Pt 500	No No
• Pt 500	No
Pt 500 according to GOST	No
Input ranges (rated values), resistors	
• 0 to 150 ohms	No
• 0 to 300 ohms	No
• 0 to 600 ohms	Yes
— Input resistance (0 to 600 ohms)	10 ΜΩ
• 0 to 3000 ohms	No
• 0 to 6000 ohms	Yes
— Input resistance (0 to 6000 ohms)	10 ΜΩ
• PTC	Yes
— Input resistance (PTC)	10 ΜΩ
Cable length	
• shielded, max.	200 m; 50 m at 50 mV
Analog value generation for the inputs	
Measurement principle	integrating
Measurement principle Integration and conversion time/resolution per channel	integrating
Integration and conversion time/resolution per channel	
Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max.	16 bit
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable	16 bit Yes
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms)	16 bit Yes 2,5 / 16,67 / 20 / 100 ms
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time	16 bit Yes
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms)	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time	16 bit Yes 2,5 / 16,67 / 20 / 100 ms
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms 4 ms (to be considered in R/RTD/U 1 to 5 V measurement)
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms 4 ms (to be considered in R/RTD/U 1 to 5 V measurement) 8 ms
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms 4 ms (to be considered in R/RTD/U 1 to 5 V measurement) 8 ms
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Smoothing of measured values	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms 4 ms (to be considered in R/RTD/U 1 to 5 V measurement) 8 ms 400 / 60 / 50 / 10 Hz
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Smoothing of measured values parameterizable Step: None	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms 4 ms (to be considered in R/RTD/U 1 to 5 V measurement) 8 ms 400 / 60 / 50 / 10 Hz
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Smoothing of measured values parameterizable Step: None Step: low	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms 4 ms (to be considered in R/RTD/U 1 to 5 V measurement) 8 ms 400 / 60 / 50 / 10 Hz Yes Yes
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Smoothing of measured values parameterizable Step: None Step: low Step: Medium	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms 4 ms (to be considered in R/RTD/U 1 to 5 V measurement) 8 ms 400 / 60 / 50 / 10 Hz Yes Yes Yes
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Smoothing of measured values parameterizable Step: None Step: None Step: Medium Step: High	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms 4 ms (to be considered in R/RTD/U 1 to 5 V measurement) 8 ms 400 / 60 / 50 / 10 Hz Yes Yes Yes Yes Yes
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Smoothing of measured values parameterizable Step: None Step: None Step: Medium Step: High Encoder	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms 4 ms (to be considered in R/RTD/U 1 to 5 V measurement) 8 ms 400 / 60 / 50 / 10 Hz Yes Yes Yes Yes Yes
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Smoothing of measured values parameterizable Step: None Step: None Step: High Encoder Connection of signal encoders	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms 4 ms (to be considered in R/RTD/U 1 to 5 V measurement) 8 ms 400 / 60 / 50 / 10 Hz Yes Yes Yes Yes Yes Yes
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Smoothing of measured values parameterizable Step: None Step: None Step: Medium Step: High Encoder Connection of signal encoders for voltage measurement	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms 4 ms (to be considered in R/RTD/U 1 to 5 V measurement) 8 ms 400 / 60 / 50 / 10 Hz Yes Yes Yes Yes Yes Yes
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Smoothing of measured values parameterizable Step: None Step: None Step: Hedium Step: High Encoder Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms 4 ms (to be considered in R/RTD/U 1 to 5 V measurement) 8 ms 400 / 60 / 50 / 10 Hz Yes Yes Yes Yes Yes Yes Yes Yes Yes Ye
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Smoothing of measured values parameterizable Step: None Step: None Step: Medium Step: High Encoder Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer for current measurement as 4-wire transducer	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms 4 ms (to be considered in R/RTD/U 1 to 5 V measurement) 8 ms 400 / 60 / 50 / 10 Hz Yes Yes Yes Yes Yes Yes Yes Yes Yes Ye
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Smoothing of measured values parameterizable Step: None Step: None Step: High Encoder Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer for current measurement as 4-wire transducer for resistance measurement with two-wire connection	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms 4 ms (to be considered in R/RTD/U 1 to 5 V measurement) 8 ms 400 / 60 / 50 / 10 Hz Yes Yes Yes Yes Yes Yes Yes Yes Yes Ye
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Integration time (ms) Basic conversion time, including integration time (ms) — additional conversion time for wire-break monitoring — additional conversion time for resistance measurement Interference voltage suppression for interference frequency f1 in Hz Smoothing of measured values parameterizable Step: None Step: None Step: Medium Step: High Encoder Connection of signal encoders for current measurement as 2-wire transducer for current measurement as 4-wire transducer for resistance measurement with two-wire	16 bit Yes 2,5 / 16,67 / 20 / 100 ms 10 / 24 / 27 / 107 ms 4 ms (to be considered in R/RTD/U 1 to 5 V measurement) 8 ms 400 / 60 / 50 / 10 Hz Yes Yes Yes Yes Yes Yes Yes Yes Yes Ye

Errors/accuracies	
Linearity error (relative to input range), (+/-)	0.1 %
Temperature error (relative to input range), (+/-)	0.006 %/K
Crosstalk between the inputs, max.	-50 dB
Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	0.1 %
Operational error limit in overall temperature range	
Voltage, relative to input range, (+/-)	0.5 %
• Current, relative to input range, (+/-)	0.5 %
Resistance, relative to input range, (+/-)	0.5 %
Resistance thermometer, relative to input range, (+/-)	Ptxxx Standard: ±1.2 K, Ptxxx Climate: ±0.8 K, Nixxx Standard: ±0.8 K, Nixxx Climate: ±0.8 K
Basic error limit (operational limit at 25 °C)	
Voltage, relative to input range, (+/-)	0.3 %
Current, relative to input range, (+/-)	0.3 %
• Resistance, relative to input range, (+/-)	0.3 %
 Resistance thermometer, relative to input range, (+/-) 	Ptxxx Standard: ±1.0 K, Ptxxx Climate: ±0.5 K, Nixxx Standard: ±0.5 K, Nixxx Climate: ±0.5 K
Interference voltage suppression for f = n x (f1 +/- 1 %), f1 =	interference frequency
 Series mode interference (peak value of interference < rated value of input range), min. 	40 dB
 Common mode voltage, max. 	4 V
Common mode interference, min.	60 dB
Interrupts/diagnostics/status information	
Diagnostics function	Yes
Alarms	
Diagnostic alarm	Yes
Limit value alarm	Yes; two upper and two lower limit values in each case
Diagnoses	
 Monitoring the supply voltage 	No
Wire-break	Yes; Only for 1 5 V, 4 20 mA, R, and RTD
Short-circuit	No
Group error	No
Overflow/underflow	Yes
Diagnostics indication LED	
• RUN LED	Yes; green LED
• ERROR LED	Yes; red LED
MAINT LED	No
 Monitoring of the supply voltage (PWR-LED) 	No
 Channel status display 	Yes; green LED
 for channel diagnostics 	Yes; red LED
for module diagnostics	Yes; red LED
Potential separation	
Potential separation channels	
 between the channels 	No
 between the channels, in groups of 	8
between the channels and backplane bus	Yes
Permissible potential difference	
between the inputs (UCM)	8 V DC
Between the inputs and MANA (UCM)	4 V DC
Isolation	
Isolation tested with	707 V DC (type test)
Ambient conditions	
Ambient temperature during operation	
horizontal installation, min.	0 °C
 horizontal installation, max. 	60 °C
• vertical installation, min.	0 °C
 vertical installation, max. 	40 °C

Altitude during operation relating to sea level	
Installation altitude above sea level, max.	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	35 mm
Height	147 mm
Depth	129 mm
Weights	
Weight, approx.	250 g

last modified: 1/19/2021 🖸