6ES7522-5EH00-0AB0

Data sheet



SIMATIC S7-1500, digital output module DQ16x24..48VUC/125V DC/0.5A ST; 16 channels in groups of 1; 0.5 A per group; substitute value: observe derating the module supports the safety-oriented shutdown of load groups up to SILCL2 acc. to EN 62061:2005 + A2:2015, and Category 3 / PL d according to EN ISO 13849-1:2015. front connector (screw terminals or push-in) to be ordered separately

General information		
Product type designation	DQ 16x24 48 V UC/125 V DC/0.5 A ST	
HW functional status	FS02	
Firmware version	V1.0.0	
 FW update possible 	Yes	
Product function		
● I&M data	Yes; I&M0 to I&M3	
 Isochronous mode 	No	
Prioritized startup	Yes	
Engineering with		
 STEP 7 TIA Portal configurable/integrated from version 	V13 SP1 / -	
 STEP 7 configurable/integrated from version 	V5.5 SP3 / -	
 PROFIBUS from GSD version/GSD revision 	V1.0 / V5.1	
PROFINET from GSD version/GSD revision	V2.3 / -	
Operating mode		
• DQ	Yes	
 DQ with energy-saving function 	No	
• PWM	No	
 Cam control (switching at comparison values) 	No	
 Oversampling 	No	
• MSO	Yes	
 Integrated operating cycle counter 	No	
Output voltage		
Rated value (DC)	24 V; 48 V, 125 V	
Rated value (AC)	24 V; 48 V (50 - 60 Hz)	
Power		
Power available from the backplane bus	2 W	
Power loss		
Power loss, typ.	3.8 W	
Digital outputs		
Type of digital output	Transistor	
Number of digital outputs	16	
Current-sinking	Yes	
Current-sourcing	Yes	
Digital outputs, parameterizable	Yes	
Limitation of inductive shutdown voltage to	200 V (suppressor diode)	

Controlling a digital input	Yes
Switching capacity of the outputs	
with resistive load, max.	0.5 A
• on lamp load, max.	40 W; At 125 V DC, 10 W at 48 V UC, 5 W at 24 V UC
Output voltage	
• for signal "1", min.	L+ (-1.0 V)
Output current	
for signal "1" rated value	0.5 A
• for signal "1" permissible range, max.	0.6 A
Output delay with resistive load	
• "0" to "1", max.	5 ms
• "1" to "0", max.	5 ms
Parallel switching of two outputs	
• for logic links	Yes
• for uprating	No
 for redundant control of a load 	Yes
Switching frequency	
with resistive load, max.	25 Hz
with inductive load, max.	0.5 Hz
• on lamp load, max.	10 Hz
Total current of the outputs	
Current per channel, max.	0.5 A
Current per group, max.	0.5 A
Current per module, max.	8 A
Cable length	
• shielded, max.	1 000 m
• unshielded, max.	600 m
Interrupts/diagnostics/status information	
Diagnostics function	No
Substitute values connectable	Yes
Alarms	166
Diagnostic alarm	No
5 Blaghootio diami	No
Maintenance interrupt	
Maintenance interrupt Diagnoses	110
Diagnoses	
Diagnoses • Monitoring the supply voltage	No
Diagnoses Monitoring the supply voltage Wire-break	No No
Diagnoses • Monitoring the supply voltage • Wire-break • Short-circuit	No
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED	No No No
Diagnoses • Monitoring the supply voltage • Wire-break • Short-circuit Diagnostics indication LED • RUN LED	No No No Yes; green LED
Diagnoses • Monitoring the supply voltage • Wire-break • Short-circuit Diagnostics indication LED • RUN LED • ERROR LED	No No No Yes; green LED Yes; red LED
Diagnoses • Monitoring the supply voltage • Wire-break • Short-circuit Diagnostics indication LED • RUN LED • ERROR LED • Monitoring of the supply voltage (PWR-LED)	No No No Yes; green LED Yes; red LED No
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display	No No No Yes; green LED Yes; red LED No Yes; green LED
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics	No No No Yes; green LED Yes; red LED No Yes; green LED No
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics	No No No Yes; green LED Yes; red LED No Yes; green LED
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation	No No No Yes; green LED Yes; red LED No Yes; green LED No
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RRROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation Potential separation channels	No No No Yes; green LED Yes; red LED No Yes; green LED No Yes; green LED No Yes; red LED
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation Potential separation channels between the channels	No No No Yes; green LED Yes; red LED No Yes; green LED No Yes; green LED No Yes; red LED
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RUN LED REROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels, in groups of	No No No Yes; green LED Yes; red LED No Yes; green LED No Yes; green LED No Yes; red LED
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels between the channels, in groups of between the channels and backplane bus	No No No Yes; green LED Yes; red LED No Yes; green LED No Yes; green LED No Yes; red LED
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels between the channels, in groups of between the channels and backplane bus Permissible potential difference	No No No Yes; green LED Yes; red LED No Yes; green LED No Yes; green LED No Yes; red LED
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RUN LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics between the channels between the channels between the channels and backplane bus Permissible potential difference between different circuits	No No No Yes; green LED Yes; red LED No Yes; green LED No Yes; green LED No Yes; red LED
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels between the channels, in groups of between the channels and backplane bus Permissible potential difference	No No No Yes; green LED Yes; red LED No Yes; green LED No Yes; green LED No Yes; red LED
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RUN LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics between the channels between the channels between the channels and backplane bus Permissible potential difference between different circuits	No No No Yes; green LED Yes; red LED No Yes; green LED No Yes; green LED No Yes; red LED
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RUN LED FRROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels between the channels and backplane bus Permissible potential difference between different circuits Isolation	No No No Yes; green LED Yes; red LED No Yes; green LED No Yes; green LED No Yes; red LED
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RUN LED FRROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics between the channels between the channels between the channels between the channels and backplane bus Permissible potential difference between different circuits Isolation Isolation	No No No Yes; green LED Yes; red LED No Yes; green LED No Yes; green LED No Yes; red LED
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RUN LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels between the channels, in groups of between the channels and backplane bus Permissible potential difference between different circuits Isolation Isolation tested with Standards, approvals, certificates	No No No Yes; green LED Yes; red LED No Yes; green LED No Yes; red LED Yes; red LED Yes 1 Yes 1 25 V DC/48 V AC
Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RUN LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics between the channels between the channels between the channels and backplane bus Permissible potential difference between different circuits Isolation Isolation tested with Standards, approvals, certificates Suitable for safety functions	No No No Yes; green LED Yes; red LED No Yes; green LED No Yes; red LED Yes 1 Yes

 Category according to ISO 13849-1 	Cat. 3	
 SILCL according to IEC 62061 	SILCL 2	
Ambient conditions		
Ambient temperature during operation		
 horizontal installation, min. 	0 °C	
 horizontal installation, max. 	60 °C	
 vertical installation, min. 	0 °C	
 vertical installation, max. 	40 °C	
Dimensions		
Width	35 mm	
Height	147 mm	
Depth	129 mm	
Weights		
Weight, approx.	230 g	
last modified:	1/16/2021 🗗	