## SIEMENS

## Data sheet

## 6ES7431-7QH00-0AB0



SIMATIC S7-400, analog input SM 431, isolated 16 Al; resolution 16 bit, U/I/Resistor/Thermocouple/Pt100 , alarm, diagnostics

	Figure sir	nilar
--	------------	-------

Supply voltage	
Load voltage L+	
Rated value (DC)	24 V; Only required for supplying 2-wire transmitters
<ul> <li>Reverse polarity protection</li> </ul>	Yes
Input current	
from load voltage L+ (without load), max.	400 mA; for 16 connected, fully controlled 2-wire transmitters
from backplane bus 5 V DC, max.	700 mA
Power loss	
Power loss, typ.	4.5 W
Analog inputs	
Number of analog inputs	16
<ul> <li>For voltage/current measurement</li> </ul>	16
<ul> <li>For resistance measurement</li> </ul>	8
permissible input voltage for voltage input (destruction limit), max.	18 V; 18 V continuous, 75 V for 1 ms (mark to space ratio 1:20)
permissible input current for current input (destruction limit), max.	40 mA
Constant measurement current for resistance-type transmitter, typ.	1.67 mA
Input ranges	
Voltage	Yes
Current	Yes
Thermocouple	Yes
Resistance thermometer	Yes
Resistance	Yes
Input ranges (rated values), voltages	
• 1 V to 5 V	Yes
— Input resistance (1 V to 5 V)	1 ΜΩ
• -1 V to +1 V	Yes
<ul> <li>Input resistance (-1 V to +1 V)</li> </ul>	1 ΜΩ
• -10 V to +10 V	Yes
<ul> <li>Input resistance (-10 V to +10 V)</li> </ul>	1 ΜΩ
• -2.5 V to +2.5 V	Yes
<ul> <li>Input resistance (-2.5 V to +2.5 V)</li> </ul>	1 ΜΩ
• -25 mV to +25 mV	Yes
<ul> <li>Input resistance (-25 mV to +25 mV)</li> </ul>	1 ΜΩ
<ul> <li>-250 mV to +250 mV</li> </ul>	Yes

	1.110
<ul> <li>Input resistance (-250 mV to +250 mV)</li> </ul>	1 ΜΩ
• -5 V to +5 V	Yes
— Input resistance (-5 V to +5 V)	1 ΜΩ
● -50 mV to +50 mV	Yes
<ul> <li>Input resistance (-50 mV to +50 mV)</li> </ul>	1 ΜΩ
<ul> <li>-500 mV to +500 mV</li> </ul>	Yes
<ul> <li>Input resistance (-500 mV to +500 mV)</li> </ul>	1 ΜΩ
<ul> <li>-80 mV to +80 mV</li> </ul>	Yes
<ul> <li>Input resistance (-80 mV to +80 mV)</li> </ul>	1 ΜΩ
Input ranges (rated values), currents	
• 0 to 20 mA	Yes
— Input resistance (0 to 20 mA)	50 Ω
<ul> <li>-10 mA to +10 mA</li> </ul>	Yes
<ul> <li>Input resistance (-10 mA to +10 mA)</li> </ul>	50 Ω
• -20 mA to +20 mA	Yes
— Input resistance (-20 mA to +20 mA)	50 Ω
• 4 mA to 20 mA	Yes
— Input resistance (4 mA to 20 mA)	50 Ω
• -5 mA to +5 mA	Yes
— Input resistance (-5 mA to +5 mA)	50 Ω
Input ranges (rated values), thermocouples	
• Туре В	Yes
— Input resistance (Type B)	1 ΜΩ
• Туре Е	Yes
— Input resistance (Type E)	1 ΜΩ
• Type J	Yes
— Input resistance (type J)	1 ΜΩ
• Type K	Yes
— Input resistance (Type K)	1 ΜΩ
• Type L	Yes
— Input resistance (Type L)	1 ΜΩ
• Type N	Yes
— Input resistance (Type N)	1 ΜΩ
• Type R	Yes
— Input resistance (Type R)	1 ΜΩ
• Type S	Yes
— Input resistance (Type S)	1 ΜΩ
• Type T	Yes
Input resistance (Type T)	1 ΜΩ
• Type U	Yes
Input resistance (Type U)	1 ΜΩ
Input ranges (rated values), resistance thermometer	
Ni 100	Yes
— Input resistance (Ni 100)	1 ΜΩ
<ul> <li>Input resistance (Nr 100)</li> <li>Ni 1000</li> </ul>	Yes
Input resistance (Ni 1000)	1 ΜΩ
• Pt 100	Yes
	res 1 MΩ
<ul><li>— Input resistance (Pt 100)</li><li>• Pt 1000</li></ul>	Yes
	res 1 MΩ
— Input resistance (Pt 1000)	
Pt 200     Input registered (Pt 200)	Yes
— Input resistance (Pt 200)	
Pt 500     Input registeres (Pt 500)	Yes
— Input resistance (Pt 500)	1 ΜΩ
Input ranges (rated values), resistors	Vac
• 0 to 48 ohms	Yes
<ul> <li>Input resistance (0 to 48 ohms)</li> </ul>	1 ΜΩ
<ul> <li>0 to 150 ohms</li> </ul>	Yes

	4.140
— Input resistance (0 to 150 ohms)	1 ΜΩ
• 0 to 300 ohms	Yes
— Input resistance (0 to 300 ohms)	1 MΩ Yes
• 0 to 600 ohms	Tes 1 MΩ
— Input resistance (0 to 600 ohms)	
• 0 to 6000 ohms	Yes; Usable up to 5000 Ohm
— Input resistance (0 to 6000 ohms) Thermocouple (TC)	1 ΜΩ
Temperature compensation — parameterizable	Yes
	Yes
— external temperature compensation with	Yes
compensations socket	
<ul> <li>— dynamic reference temperature value</li> </ul>	Yes
Characteristic linearization	
parameterizable	Yes
— for thermocouples	Type B, E, J, K, L, N, R, S, T, U
— for resistance thermometer	Pt100, Pt200, Pt500, Pt1000, Ni100, Ni1000
Cable length	
• shielded, max.	200 m; 50 m with thermocouples and input ranges $\leq$ 80 mV
Analog value generation for the inputs	
Integration and conversion time/resolution per channel	
<ul> <li>Resolution with overrange (bit including sign), max.</li> </ul>	16 bit; 16 / 16 / 16
<ul> <li>Integration time, parameterizable</li> </ul>	Yes
<ul> <li>Basic conversion time (ms)</li> </ul>	6 / 20,1 / 23,5 ms
<ul> <li>Integration time (ms)</li> </ul>	2,5 / 16,7 / 20 ms
<ul> <li>Interference voltage suppression for interference</li> </ul>	400 / 60 / 50 Hz
frequency f1 in Hz	
Encoder	
Connection of signal encoders	
<ul> <li>for voltage measurement</li> </ul>	Yes; possible
<ul><li>for voltage measurement</li><li>for current measurement as 2-wire transducer</li></ul>	Yes
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> </ul>	Yes Yes
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> </ul>	Yes Yes; Line resistances are also measured
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire</li> </ul>	Yes Yes
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire</li> </ul>	Yes Yes; Line resistances are also measured
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire</li> </ul>	Yes Yes; Line resistances are also measured Yes
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> </ul>	Yes Yes; Line resistances are also measured Yes
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>for resistance measurement with four-wire connection</li> </ul>	Yes Yes; Line resistances are also measured Yes
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>for resistance measurement with four-wire connection</li> </ul>	Yes Yes; Line resistances are also measured Yes Yes
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>for resistance measurement with four-wire connection</li> </ul>	Yes Yes; Line resistances are also measured Yes Yes 0.3 %; ±0.3 % at ±250 mV, ±500 mV, ±1 V, ±2.5 V, ±5 V, 1 to 5 V, ±10
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>for resistance measurement with reservice to a service the service of the service of</li></ul>	Yes Yes; Line resistances are also measured Yes Yes O.3 %; ±0.3 % at ±250 mV, ±500 mV, ±1 V, ±2.5 V, ±5 V, 1 to 5 V, ±10 V; ±0.31 % at ±80 mV; ±0.32 % at ±50 mV; ±0.35 % at ±25 mV O.3 %; at 0 to 20 mA, ±5 mA, ±10 mA, ±20 mA, 4 to 20 mA 0.3 %; ±0.3% at 0 to 48 Ohm (4-conductor measurement), 0 to 150
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> </ul>	Yes Yes; Line resistances are also measured Yes Yes Yes 0.3 %; ±0.3 % at ±250 mV, ±500 mV, ±1 V, ±2.5 V, ±5 V, 1 to 5 V, ±10 V; ±0.31 % at ±80 mV; ±0.32 % at ±50 mV; ±0.35 % at ±25 mV 0.3 %; at 0 to 20 mA, ±5 mA, ±10 mA, ±20 mA, 4 to 20 mA 0.3 %; ±0.3% at 0 to 48 Ohm (4-conductor measurement), 0 to 150 Ohm (4-conductor measurement), 0 to 300 Ohm (4-conductor
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> </ul>	Yes Yes; Line resistances are also measured Yes Yes Yes 0.3 %; ±0.3 % at ±250 mV, ±500 mV, ±1 V, ±2.5 V, ±5 V, 1 to 5 V, ±10 V; ±0.31 % at ±80 mV; ±0.32 % at ±50 mV; ±0.35 % at ±25 mV 0.3 %; at 0 to 20 mA, ±5 mA, ±10 mA, ±20 mA, 4 to 20 mA 0.3 %; ±0.3% at 0 to 48 Ohm (4-conductor measurement), 0 to 150 Ohm (4-conductor measurement), 0 to 300 Ohm (4-conductor measurement), 0 to 600 Ohm (4-conductor measurement), 0 to 5000
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> </ul>	Yes Yes; Line resistances are also measured Yes Yes Yes $(3.3\%; \pm 0.3\% at \pm 250 \text{ mV}, \pm 500 \text{ mV}, \pm 1 \text{ V}, \pm 2.5 \text{ V}, \pm 5 \text{ V}, 1 \text{ to 5 V}, \pm 10 \text{ V}, \pm 0.31\% at \pm 80 \text{ mV}; \pm 0.32\% at \pm 50 \text{ mV}; \pm 0.35\% at \pm 25 \text{ mV}$ $(3.3\%; \pm 0.3\% at 0 \text{ to } 20 \text{ mA}, \pm 5 \text{ mA}, \pm 10 \text{ mA}, \pm 20 \text{ mA}, 4 \text{ to } 20 \text{ mA}$ $(3.3\%; \pm 0.3\% at 0 \text{ to } 48 \text{ Ohm}$ (4-conductor measurement), 0 to 150 Ohm (4-conductor measurement), 0 to 300 Ohm (4-conductor measurement), 0 to 5000 Ohm (4-conductor measurement), 0 to 5000 Ohm (4-conductor measurement), 0 to 600 Ohm); \pm 0.4\% at 0 to 300 Ohm (3-conductor measurement), 0 to 600 Ohm (3-co
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> </ul>	Yes Yes; Line resistances are also measured Yes Yes Yes Yes 0.3 %; ±0.3 % at ±250 mV, ±500 mV, ±1 V, ±2.5 V, ±5 V, 1 to 5 V, ±10 V; ±0.31 % at ±80 mV; ±0.32 % at ±50 mV; ±0.35 % at ±25 mV 0.3 %; at 0 to 20 mA, ±5 mA, ±10 mA, ±20 mA, 4 to 20 mA 0.3 %; ±0.3% at 0 to 48 Ohm (4-conductor measurement), 0 to 150 Ohm (4-conductor measurement), 0 to 300 Ohm (4-conductor measurement), 0 to 600 Ohm (4-conductor measurement), 0 to 5000 Ohm (4-conductor measurement), 0 to 600 Ohm); ±0.4% at 0 to 300 Ohm (3-conductor measurement), 0 to 600 Ohm (3-conductor measurement), 0 to 5000 Ohm (3-conductor measurement), 0 to 5000
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>voltage, relative to input range, (+/-)</li> <li>Resistance, relative to input range, (+/-)</li> </ul>	Yes Yes; Line resistances are also measured Yes Yes Yes Yes
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> </ul>	Yes Yes; Line resistances are also measured Yes Yes Yes Yes 0.3 %; ±0.3 % at ±250 mV, ±500 mV, ±1 V, ±2.5 V, ±5 V, 1 to 5 V, ±10 V; ±0.31 % at ±80 mV; ±0.32 % at ±50 mV; ±0.35 % at ±25 mV 0.3 %; at 0 to 20 mA, ±5 mA, ±10 mA, ±20 mA, 4 to 20 mA 0.3 %; ±0.3% at 0 to 48 Ohm (4-conductor measurement), 0 to 150 Ohm (4-conductor measurement), 0 to 300 Ohm (4-conductor measurement), 0 to 600 Ohm (4-conductor measurement), 0 to 5000 Ohm (4-conductor measurement), 0 to 600 Ohm); ±0.4% at 0 to 300 Ohm (3-conductor measurement), 0 to 600 Ohm (3-conductor measurement), 0 to 5000 Ohm (3-conductor measurement), 0 to 5000
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>for resistance measurement with respect to input range, (+/-)</li> <li>Resistance thermometer, relative to input range, (+/-)</li> </ul>	Yes Yes; Line resistances are also measured Yes Yes Yes O.3 %; ±0.3 % at ±250 mV, ±500 mV, ±1 V, ±2.5 V, ±5 V, 1 to 5 V, ±10 V; ±0.31 % at ±80 mV; ±0.32 % at ±50 mV; ±0.35 % at ±25 mV O.3 %; at 0 to 20 mA, ±5 mA, ±10 mA, ±20 mA, 4 to 20 mA O.3 %; ±0.3% at 0 to 48 Ohm (4-conductor measurement), 0 to 150 Ohm (4-conductor measurement), 0 to 300 Ohm (4-conductor measurement), 0 to 600 Ohm (4-conductor measurement), 0 to 5000 Ohm (4-conductor measurement), 0 to 600 Ohm); ±0.4% at 0 to 300 Ohm (3-conductor measurement), 0 to 600 Ohm (3-conductor measurement), 0 to 5000 Ohm (3-conductor measurement, in range of 6000 Ohm); O.4 %
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>voltage, relative to input range, (+/-)</li> <li>Resistance, relative to input range, (+/-)</li> </ul>	Yes Yes; Line resistances are also measured Yes Yes Yes $\begin{array}{c} 0.3 \ \%; \pm 0.3 \ \% \ at \pm 250 \ mV, \pm 500 \ mV, \pm 1 \ V, \pm 2.5 \ V, \pm 5 \ V, 1 \ to 5 \ V, \pm 10 \ V; \pm 0.31 \ \% \ at \pm 80 \ mV; \pm 0.32 \ \% \ at \pm 50 \ mV; \pm 0.35 \ \% \ at \pm 25 \ mV \ 0.3 \ \%; at 0 \ to 20 \ mA, \pm 5 \ mA, \pm 10 \ mA, \pm 20 \ mA, 4 \ to 20 \ mA \ 0.3 \ \%; \pm 0.3\% \ at 0 \ to 48 \ Ohm (4-conductor measurement), 0 \ to 150 \ Ohm (4-conductor measurement), 0 \ to 300 \ Ohm (4-conductor measurement), 0 \ to 5000 \ Ohm (3-conductor measurement), 0 \ to 600 \ Ohm (3-conductor measurement), 0 \ to 5000 \ Ohm (3-conductor measurement$
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>Voltage, relative to input range, (+/-)</li> <li>Resistance, relative to input range, (+/-)</li> <li>Resistance thermometer, relative to input range, (+/-)</li> <li>Thermocouple, relative to input range, (+/-)</li> </ul>	Yes Yes; Line resistances are also measured Yes Yes Yes 0.3 %; ±0.3 % at ±250 mV, ±500 mV, ±1 V, ±2.5 V, ±5 V, 1 to 5 V, ±10 V; ±0.31 % at ±80 mV; ±0.32 % at ±50 mV; ±0.35 % at ±25 mV 0.3 %; at 0 to 20 mA, ±5 mA, ±10 mA, ±20 mA, 4 to 20 mA 0.3 %; ±0.3% at 0 to 48 Ohm (4-conductor measurement), 0 to 150 Ohm (4-conductor measurement), 0 to 300 Ohm (4-conductor measurement), 0 to 600 Ohm (4-conductor measurement), 0 to 5000 Ohm (4-conductor measurement), 0 to 600 Ohm); ±0.4% at 0 to 300 Ohm (3-conductor measurement), 0 to 600 Ohm); ±0.4% at 0 to 300 Ohm (3-conductor measurement), 0 to 600 Ohm (3-conductor measurement), 0 to 5000 Ohm (3-conductor measurement, in range of 6000 Ohm); 0.4 % TC Type B (±11.5 K), TC Type R (±7.3 K), TC Type S (±8.3 K), TC Type
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>Voltage, relative to input range, (+/-)</li> <li>Resistance, relative to input range, (+/-)</li> <li>Resistance thermometer, relative to input range, (+/-)</li> <li>Thermocouple, relative to input range, (+/-)</li> </ul> Basic error limit (operational limit at 25 °C)	Yes Yes; Line resistances are also measured Yes Yes Yes Yes $\begin{array}{c} 0.3 \ \%; \pm 0.3 \ \% \ at \pm 250 \ mV, \pm 500 \ mV, \pm 1 \ V, \pm 2.5 \ V, \pm 5 \ V, 1 \ to 5 \ V, \pm 10 \ V; \pm 0.31 \ \% \ at \pm 80 \ mV; \pm 0.32 \ \% \ at \pm 50 \ mV; \pm 0.35 \ \% \ at \pm 25 \ mV \ 0.3 \ \%; at 0 \ to 20 \ mA, \pm 5 \ mA, \pm 10 \ mA, \pm 20 \ mA, 4 \ to 20 \ mA \ 0.3 \ \%; \pm 0.3\% \ at 0 \ to 48 \ Ohm (4-conductor measurement), 0 \ to 150 \ Ohm (4-conductor measurement), 0 \ to 300 \ Ohm (4-conductor measurement), 0 \ to 5000 \ Ohm (4-conductor measurement), 0 \ to 5000 \ Ohm (4-conductor measurement), 0 \ to 5000 \ Ohm (3-conductor measur$
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>Voltage, relative to input range, (+/-)</li> <li>Resistance thermometer, relative to input range, (+/-)</li> <li>Resistance thermometer, relative to input range, (+/-)</li> <li>Thermocouple, relative to input range, (+/-)</li> </ul> Basic error limit (operational limit at 25 °C) <ul> <li>Voltage, relative to input range, (+/-)</li> </ul>	Yes Yes; Line resistances are also measured Yes Yes Yes Yes $\begin{array}{c} 0.3 \ \%; \pm 0.3 \ \% \ at \pm 250 \ mV, \pm 500 \ mV, \pm 1 \ V, \pm 2.5 \ V, \pm 5 \ V, 1 \ to 5 \ V, \pm 10 \ V; \pm 0.31 \ \% \ at \pm 80 \ mV; \pm 0.32 \ \% \ at \pm 50 \ mV; \pm 0.35 \ \% \ at \pm 25 \ mV \ 0.3 \ \%; \ at 0 \ to 20 \ mA, \pm 5 \ mA, \pm 10 \ mA, \pm 20 \ mA, 4 \ to 20 \ mA \ 0.3 \ \%; \pm 0.3\% \ at 0 \ to 4 \ 80 \ hm (4-conductor measurement), 0 \ to 150 \ Ohm (4-conductor measurement), 0 \ to 5000 \ Ohm (3-conductor measurement), 0 \ to 6000 \ Ohm (3-conductor measurement), 0 \ to 6000 \ Ohm (3-conductor measurement), 0 \ to 5000 \ Ohm (3-conductor measurement), 0 \ to 6000 \ Ohm); 0.4 \ \%$ TC Type B ( $\pm 11.5 \text{ K}$ ), TC Type R ( $\pm 7.3 \text{ K}$ ), TC Type S ( $\pm 8.3 \text{ K}$ ), TC Type T ( $\pm 1.7 \text{ K}$ ), TC Type E ( $\pm 3.2 \text{ K}$ ), TC Type I ( $\pm 4.2 \text{ K}$ ), TC Type N ( $\pm 4.4 \text{ K}$ ) 0.15 \ \%; $\pm 0.15\%$ at $\pm 250 \text{ mV}$ , $\pm 500 \text{ mV}$ , $\pm 1 \text{ V}$ , $\pm 2.5 \text{ V}$ , $\pm 5 \text{ V}$ , 1 V to 5 V, $\pm 10 \text{ V}$ ; $\pm 0.17\%$ at $\pm 80 \text{ mV}$ ; $\pm 0.19\%$ at $\pm 50 \text{ mV}$ ; $\pm 0.23\%$ at $\pm 25 \text{ mV}$
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>Voltage, relative to input range, (+/-)</li> <li>Resistance thermometer, relative to input range, (+/-)</li> <li>Thermocouple, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Voltage, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> </ul>	Yes Yes; Line resistances are also measured Yes Yes Yes Yes $\begin{array}{c} 0.3 \ \%; \pm 0.3 \ \% \ at \pm 250 \ mV, \pm 500 \ mV, \pm 1 \ V, \pm 2.5 \ V, \pm 5 \ V, 1 \ to 5 \ V, \pm 10 \ V, \pm 0.31 \ \% \ at \pm 80 \ mV; \pm 0.32 \ \% \ at \pm 50 \ mV; \pm 0.35 \ \% \ at \pm 25 \ mV \ 0.3 \ \%; \ at 0 \ to 20 \ mA, \pm 5 \ mA, \pm 10 \ mA, \pm 20 \ mA, 4 \ to 20 \ mA \ 0.3 \ \%; \ \pm 0.3\% \ at 0 \ to 48 \ Ohm (4-conductor measurement), 0 \ to 150 \ Ohm (4-conductor measurement), 0 \ to 300 \ Ohm (4-conductor measurement), 0 \ to 5000 \ Ohm (4-conductor measurement), 0 \ to 5000 \ Ohm (3-conductor measurement), 0 \ to 5000 \ Ohm); 0.4 \ \%$
<ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>for resistance measurement with two-wire connection</li> <li>for resistance measurement with three-wire connection</li> <li>for resistance measurement with four-wire connection</li> <li>Voltage, relative to input range, (+/-)</li> <li>Resistance thermometer, relative to input range, (+/-)</li> <li>Resistance thermometer, relative to input range, (+/-)</li> <li>Thermocouple, relative to input range, (+/-)</li> </ul> Basic error limit (operational limit at 25 °C) <ul> <li>Voltage, relative to input range, (+/-)</li> </ul>	Yes Yes; Line resistances are also measured Yes Yes Yes Yes $\begin{array}{c} 0.3 \ \%; \pm 0.3 \ \% \ at \pm 250 \ mV, \pm 500 \ mV, \pm 1 \ V, \pm 2.5 \ V, \pm 5 \ V, 1 \ to 5 \ V, \pm 10 \ V; \pm 0.31 \ \% \ at \pm 80 \ mV; \pm 0.32 \ \% \ at \pm 50 \ mV; \pm 0.35 \ \% \ at \pm 25 \ mV \ 0.3 \ \%; \ at 0 \ to 20 \ mA, \pm 5 \ mA, \pm 10 \ mA, \pm 20 \ mA, 4 \ to 20 \ mA \ 0.3 \ \%; \pm 0.3\% \ at 0 \ to 4 \ 80 \ hm (4-conductor measurement), 0 \ to 150 \ Ohm (4-conductor measurement), 0 \ to 5000 \ Ohm (3-conductor measurement), 0 \ to 6000 \ Ohm (3-conductor measurement), 0 \ to 6000 \ Ohm (3-conductor measurement), 0 \ to 5000 \ Ohm (3-conductor measurement), 0 \ to 6000 \ Ohm); 0.4 \ \%$ TC Type B ( $\pm 11.5 \text{ K}$ ), TC Type R ( $\pm 7.3 \text{ K}$ ), TC Type S ( $\pm 8.3 \text{ K}$ ), TC Type T ( $\pm 1.7 \text{ K}$ ), TC Type E ( $\pm 3.2 \text{ K}$ ), TC Type I ( $\pm 4.2 \text{ K}$ ), TC Type N ( $\pm 4.4 \text{ K}$ ) 0.15 \ \%; $\pm 0.15\%$ at $\pm 250 \text{ mV}$ , $\pm 500 \text{ mV}$ , $\pm 1 \text{ V}$ , $\pm 2.5 \text{ V}$ , $\pm 5 \text{ V}$ , 1 V to 5 V, $\pm 10 \text{ V}$ ; $\pm 0.17\%$ at $\pm 80 \text{ mV}$ ; $\pm 0.19\%$ at $\pm 50 \text{ mV}$ ; $\pm 0.23\%$ at $\pm 25 \text{ mV}$

	measurement), 0 to 5000 ohms (4-conductor measurement, in range of 6000 ohms); ±0.3 % at 0 to 300 ohms (3-conductor measurement), 0 to 600 ohms (3-conductor measurement), 0 to 5000 ohms (3-conductor measurement, in range of 6000 ohms)
<ul> <li>Resistance thermometer, relative to input range, (+/-)</li> </ul>	0.3 %
• Thermocouple, relative to input range, (+/-)	TC Type B (±7.6 K), TC Type R (±4.8 K) TC Type S (±5.4 K), TC Type T (±1.1 K), TC Type E (±1.8 K), TC Type J (±2.3 K), TC Type K (±3.4 K), TC Type U (±1.7 K), TC Type L (±2.3 K), TC Type N (±2.6 K)
Interrupts/diagnostics/status information	
Diagnostics function	Yes; Parameterizable
Alarms	
Diagnostic alarm	Yes; Parameterizable
Limit value alarm	Yes; Parameterizable
Hardware interrupt	Yes; Parameterizable
Diagnoses	
<ul> <li>Diagnostic information readable</li> </ul>	Yes
Diagnostics indication LED	
<ul> <li>internal fault INTF (red)</li> </ul>	Yes
<ul> <li>external fault EXTF (red)</li> </ul>	Yes
Potential separation	
Potential separation analog inputs	
<ul> <li>Potential separation analog inputs</li> </ul>	Yes; internal/external
<ul> <li>between the channels</li> </ul>	No
<ul> <li>between the channels and backplane bus</li> </ul>	Yes
<ul> <li>Between the channels and load voltage L+</li> </ul>	Yes
Isolation	
Isolation tested with	2 120 V DC between bus and L+/M; 2 120 V DC between bus and analog section; 500 V DC between bus and local ground; 500 V DC between analog section and L+/M; 2 120 V DC between analog section and local ground; 2 120 V DC between L+/M and local ground
Dimensions	
Width	25 mm
Height	290 mm
Depth	210 mm
Weights	
Weight, approx.	500 g

last modified:

3/2/2021 🖸