6ES7313-5BG04-0AB0

Data sheet



SIMATIC S7-300, CPU 313C, Compact CPU with MPI, 24 DI/16 DO, 4 AI, 2 AO, 1 Pt100, 3 high-speed counters (30 kHz), Integr. power supply 24 V DC, work memory 128 KB, Front connector (2x 40-pole) and Micro Memory Card required

General information	
Firmware version	V3.3
Engineering with	
Programming package	STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with HSP 203
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
external protection for power supply lines (recommendation)	Miniature circuit breaker, type C; min. 2 A; miniature circuit breaker type B, min. 4 A
Mains buffering	
 Mains/voltage failure stored energy time 	5 ms
Repeat rate, min.	1 s
Load voltage L+	
Digital inputs	
— Rated value (DC)	24 V
 Reverse polarity protection 	Yes
Digital outputs	
— Rated value (DC)	24 V
 Reverse polarity protection 	No
Input current	
Current consumption (rated value)	650 mA
Current consumption (in no-load operation), typ.	150 mA
Inrush current, typ.	5 A
l²t	0.7 A ² ·s
Digital inputs	
 from load voltage L+ (without load), max. 	80 mA
Digital outputs	
 from load voltage L+, max. 	50 mA
Power loss	
Power loss, typ.	12 W
Memory	
Work memory	
• integrated	128 kbyte
• expandable	No
Load memory	
Plug-in (MMC)	Yes

a Plug in (MMC) may	8 Mbyte
Plug-in (MMC), max. Data management on MMC (after lest.)	
 Data management on MMC (after last programming), min. 	10 y
Backup	
• present	Yes; Guaranteed by MMC (maintenance-free)
without battery	Yes; Program and data
CPU processing times	100, 110gram and data
	0.07.00
for bit operations, typ.	0.07 μs
for word operations, typ.	0.15 μs
for fixed point arithmetic, typ.	0.2 µs
for floating point arithmetic, typ.	0.72 µs
CPU-blocks	
Number of blocks (total)	1 024; (DBs, FCs, FBs); the maximum number of loadable blocks can be reduced by the MMC used.
DB	be reduced by the winter dised.
Number, max.	1 024; Number range: 1 to 16000
• Size, max.	64 kbyte
FB	04 kbyte
• Number, max.	1 024; Number range: 0 to 7999
• Size, max.	64 kbyte
	1.024: Number range: 0 to 7000
Number, max. Size max.	1 024; Number range: 0 to 7999
• Size, max.	64 kbyte
	and in the street link
Number, max.	see instruction list
Size, max. Number of free puels ORs.	64 kbyte
Number of free cycle OBs	1; OB 1
 Number of time alarm OBs 	1; OB 10
 Number of delay alarm OBs 	2; OB 20, 21
 Number of cyclic interrupt OBs 	4; OB 32, 33, 34, 35
 Number of process alarm OBs 	1; OB 40
 Number of startup OBs 	1; OB 100
 Number of asynchronous error OBs 	4; OB 80, 82, 85, 87
 Number of synchronous error OBs 	2; OB 121, 122
Nesting depth	
per priority class	16
 additional within an error OB 	4
Counters, timers and their retentivity	
S7 counter	
Number	256
Retentivity	
— adjustable	Yes
— lower limit	0
— upper limit — upper limit	255
— upper illilit — preset	Z 0 to Z 7
Counting range	20021
— lower limit	0
	0
— upper limit	999
IEC counter	Voc
• present	Yes
• Type	SFB
• Number	Unlimited (limited only by RAM capacity)
S7 times	272
• Number	256
Retentivity	
— adjustable	Yes
— lower limit	0
— upper limit	255

— preset	No retentivity
Time range	
— lower limit	10 ms
— upper limit	9 990 s
IEC timer	
• present	Yes
• Type	SFB
Number	Unlimited (limited only by RAM capacity)
Data areas and their retentivity	
Retentive data area (incl. timers, counters, flags), max.	64 kbyte
Flag	
Size, max.	256 byte
 Retentivity available 	Yes; MB 0 to MB 255
 Retentivity preset 	MB 0 to MB 15
Number of clock memories	8; 1 memory byte
Data blocks	
 Retentivity adjustable 	Yes; via non-retain property on DB
Retentivity preset	Yes
Local data	
per priority class, max.	32 kbyte; Max. 2048 bytes per block
Address area	
I/O address area	
• Inputs	1 024 byte
Outputs	1 024 byte
of which distributed	
— Inputs	none
— Outputs	none
Process image	4 004 b. t-
• Inputs	1 024 byte
Outputs Inputs adjustable	1 024 byte
Inputs, adjustableOutputs, adjustable	1 024 byte
Inputs, adjustable Inputs, default	1 024 byte 128 byte
Outputs, default	128 byte
Default addresses of the integrated channels	120 byte
Default addresses of the integrated charmers Digital inputs	124.0 to 126.7
— Digital outputs	124.0 to 125.7
— Analog inputs	752 to 761
— Analog outputs	752 to 755
Digital channels	102.00100
• Inputs	1 016
— of which central	1 016
Outputs	1 008
— of which central	1 008
Analog channels	
• Inputs	253
— of which central	253
Outputs	250
— of which central	250
Hardware configuration	
Number of expansion units, max.	3
Number of DP masters	
• integrated	none
• via CP	4
Number of operable FMs and CPs (recommended)	
• FM	8
• CP, PtP	8
• CP, LAN	6

Dools	
Rack	A
Racks, max. Madulas par rack may.	4 0. la real/ 2 may 7
Modules per rack, max.	8; In rack 3 max. 7
Clock	
Clock	V
Hardware clock (real-time)	Yes
retentive and synchronizable	Yes
Backup time	6 wk; At 40 °C ambient temperature
 Deviation per day, max. 	10 s; Typ.: 2 s
 Behavior of the clock following POWER-ON 	Clock continues running after POWER OFF
Behavior of the clock following expiry of backup period	Clock continues to run with the time at which the power failure occurred
period Operating hours counter	
Number	1
Range of values	0 to 2^31 hours (when using SFC 101)
-	1 h
Granularity retentive	
Clock synchronization	Yes; Must be restarted at each restart
·	Von
supported to MPL master.	Yes Yes
• to MPI, master	Yes
• to MPI, slave	
• in AS, master	Yes
• in AS, slave	No
ligital inputs	
Number of digital inputs	24
of which inputs usable for technological functions	12
integrated channels (DI)	24
Input characteristic curve in accordance with IEC 61131, type 1	Yes
Number of simultaneously controllable inputs	
horizontal installation	
— up to 40 °C, max.	24
— up to 60 °C, max.	12
vertical installation	
— up to 40 °C, max.	12
Input voltage	
 Rated value (DC) 	24 V
● for signal "0"	-3 to +5V
• for signal "1"	+15 to +30 V
Input current	
• for signal "1", typ.	8 mA
Input delay (for rated value of input voltage)	
for standard inputs	
— parameterizable	Yes; 0.1 / 0.3 / 3 / 15 ms (You can reconfigure the input delay of the standard inputs during program runtime. Please note that under certain circumstances your newly set filter time may not be effective until the next filter cycle.)
— Rated value	3 ms
for technological functions	
— at "0" to "1", max.	16 μs; Minimum pulse width/minimum pause between pulses at maximum counting frequency
Cable length	
• shielded, max.	1 000 m; 100 m for technological functions
• unshielded, max.	600 m; for technological functions: No
for technological functions	
— shielded, max.	100 m; at maximum count frequency
— unshielded, max.	not allowed
Digital outputs	
Number of digital outputs	16
	•

 of which high-speed outputs 	4; Notice: You cannot connect the fast outputs of your CPU in parallel
integrated channels (DO)	16
Short-circuit protection	Yes; Clocked electronically
Response threshold, typ.	1 A
Limitation of inductive shutdown voltage to	L+ (-48 V)
Controlling a digital input	Yes
Switching capacity of the outputs	100
• on lamp load, max.	5 W
Load resistance range	
• lower limit	48 Ω
• upper limit	4 kΩ
Output voltage	· · · · ·
• for signal "1", min.	L+ (-0.8 V)
Output current	- ()
for signal "1" rated value	500 mA
• for signal "1" permissible range, min.	5 mA
• for signal "1" permissible range, max.	0.6 A
• for signal "1" minimum load current	5 mA
• for signal "0" residual current, max.	0.5 mA
Parallel switching of two outputs	
• for uprating	No
for redundant control of a load	Yes
Switching frequency	166
with resistive load, max.	100 Hz
with resistive load, max. with inductive load, max.	0.5 Hz
• on lamp load, max.	100 Hz
of the pulse outputs, with resistive load, max.	2.5 kHz
Total current of the outputs (per group)	2.0 M 12
horizontal installation	
— up to 40 °C, max.	3 A
— up to 60 °C, max.	2 A
vertical installation	
— up to 40 °C, max.	2 A
Cable length	
• shielded, max.	1 000 m
• unshielded, max.	600 m
Analog inputs	000 III
Number of analog inputs	4
For voltage/current measurement	4
 For resistance/resistance thermometer measurement 	1
integrated channels (AI)	5; 4x current/voltage, 1x resistance
permissible input voltage for current input (destruction	5 V; Permanent
limit), max.	5., Officiality
permissible input voltage for voltage input (destruction limit), max.	30 V; Permanent
permissible input current for voltage input (destruction limit), max.	0.5 mA; Permanent
permissible input current for current input (destruction limit), max.	50 mA; Permanent
Electrical input frequency, max.	400 Hz
No-load voltage for resistance-type transmitter, typ.	3.3 V
Constant measurement current for resistance-type transmitter, typ.	1.25 mA
Technical unit for temperature measurement adjustable	Yes; Degrees Celsius / degrees Fahrenheit / Kelvin
Input ranges	
Voltage	Yes; ±10 V / 100 kΩ; 0 V to 10 V / 100 kΩ
• Current	Yes; ± 20 mA / 100 Ω ; 0 mA to 20 mA / 100 Ω ; 4 mA to 20 mA / 100 Ω
Resistance thermometer	Yes; Pt 100 / 10 MΩ
Resistance	Yes; 0 Ω to 600 Ω / 10 MΩ

Input ranges (rated values), voltages	
• 0 to +10 V	Yes
— Input resistance (0 to 10 V)	100 kΩ
Input ranges (rated values), currents	
• 0 to 20 mA	Yes
— Input resistance (0 to 20 mA)	100 Ω
• -20 mA to +20 mA	Yes
— Input resistance (-20 mA to +20 mA)	100 Ω
• 4 mA to 20 mA	Yes
— Input resistance (4 mA to 20 mA)	100 Ω
Input ranges (rated values), resistance thermometer	
• Pt 100	Yes
— Input resistance (Pt 100)	10 ΜΩ
Input ranges (rated values), resistors	
• 0 to 600 ohms	Yes
— Input resistance (0 to 600 ohms)	10 ΜΩ
Thermocouple (TC)	
Temperature compensation	
— parameterizable	No
Characteristic linearization	
parameterizable	Yes; by software
— for resistance thermometer	Pt 100
Cable length	
• shielded, max.	100 m
Analog outputs	
Number of analog outputs	2
integrated channels (AO)	2
Voltage output, short-circuit protection	Yes
Voltage output, short-circuit current, max.	55 mA
Current output, no-load voltage, max.	14 V
Output ranges, voltage	
• 0 to 10 V	Yes
• -10 V to +10 V	Yes
Output ranges, current	
• 0 to 20 mA	Yes
• -20 mA to +20 mA	Yes
• 4 mA to 20 mA	Yes
Connection of actuators	
 for voltage output two-wire connection 	Yes; Without compensation of the line resistances
 for voltage output four-wire connection 	No
for current output two-wire connection	Yes
Load impedance (in rated range of output)	
with voltage outputs, min.	1 kΩ
 with voltage outputs, capacitive load, max. 	0.1 μF
with current outputs, max.	300 Ω
with current outputs, inductive load, max.	0.1 mH
Destruction limits against externally applied voltages and cur	rrents
 Voltages at the outputs towards MANA 	16 V; Permanent
Current, max.	50 mA; Permanent
Cable length	
• shielded, max.	200 m
Analog value generation for the inputs	
Measurement principle	Actual value encryption (successive approximation)
Integration and conversion time/resolution per channel	
• Resolution with overrange (bit including sign), max.	12 bit
Integration time, parameterizable	Yes; 16.6 / 20 ms
 Interference voltage suppression for interference 	50 / 60 Hz
frequency f1 in Hz	

Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Setting time For resistive load For resistive load For resistive load For voltage measurement For voltage measurement as 2-wire transducer For current measurement as 2-wire transducer For current measurement as 2-wire transducer For current measurement with two-wire Connection For resistance measurement with twe-wire Connection For resistance measurement with twe-wire Connection For resistance measurement with four-wire Connectable encoders Fungerature error (relative to input range), (+/-) Constalt between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Constalt between the input range, (+/-) Fungerature error (relative to output range), (+/-) Fungerature error (relative to input range), (+/-) Fungerature error (relative to input range), (+/-) Fungerature error (relative to input range, (+/-) Fungerature error interior in overall temperature range Funderation in overall tempe		
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Setting time for resistive load for capacitive load for inductive load for inductive load for outpact measurement for current measurement as 2-wire transducer for current measurement as 4-wire transducer for resistance measurement with throe-wire connection for resistance measurement with three-wire connection for resistance measurement with four-wire connection Connectable encoders 2-wire sensor —permissible quiescent current (2-wire sensor). max. Errors/accuracles Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Linearity error (relative to output range, tendoutled to 10 to 50 dB Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range, (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range, (+/-) Crosstalk between the outputs, min. Go dB Repeat accuracy in steady state at 25 °C (relative to output range, (+/-) Crosstalk between the outputs, min. Freperature error (relative to output range, (+/-) Crosstalk between the output range, (+/-) Crosstalk between the output range, (+/-) Crosstalk between the output range, (+/-) Resistance, relative to input range, (+/-) Crosstalk between the output range, (+/-) Crosstalk be	Time constant of the input filter	0.38 ms
Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time • for resistive load • for capacitive load • for orapacitive load • for inductive load • for voltage measurement • for voltage measurement as 2-wire transducer • for current measurement as 4-wire transducer • for current measurement as 4-wire transducer • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection • for four seasurement with four-wire connection • four feasurement with four-wire connection • four feasurement with four-wire connection • four feasurement feasurement with four-wire connection • four feasurement feasurem	released)	1 ms
Resolution with overrange (bit including sign), max. Conversion time (per channet) 1 ms Settling time 1 for resistive load 1 for capacitive load 2 for inductive load 5 for resistive load 5 for capacitive load 5 for capacitive load 5 for current measurement 6 for current measurement as 2-wire transducer 6 for current measurement as 4-wire transducer 7 for current measurement as 4-wire transducer 8 for resistance measurement with three-wire connection 9 for resistance measurement with four-wire connection Connectable encoders 2 -wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracios Temperature error (relative to input range), (+/-) Constalk between the inputs, min. Ropeat accuracy in steady state at 25 °C (relative to input range), (+/-) Cutput ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-) Limearity error (relative to output range), (+/-) Crosstalk between the inputs, min. Ropeat accuracy in steady state at 25 °C (relative to output range), (+/-) 1 memperature error (relative to output range), (+/-) 2 memperature error (relative to output range), (+/-) 2 memperature error (relative to output range), (+/-) 1 memperature error (relative to output range), (+/-) 1 memperature error (relative to output range), (+/-) 2 memperature error (relative to output range), (+/-) 3 memperature error (relative to output range), (+/-) 4 memperature error (relative to output range), (+/-) 5 memperature error (relative to output range), (+/-) 6 memperature error (relative to input range, (+/-) 6 memperature error (relative to input range, (+/-) 6 memperature error (relative to input range, (+/-) 7 memperature error (relative to input range, (+/-) 8 memperature error (relative to output range, (+/-) 9 memperature error (relative to input range, (+/-) 9 memperature error (relative to input range,	Analog value generation for the outputs	
Setting time • for resistive load • for capacitive load • for capacitive load • for capacitive load • for capacitive load • for inductive load • for or capacitive load • for or capacitive load • for or capacitive load • for woltage measurement • for voltage measurement as 2-wire transducer • for current measurement as 4-wire transducer • for current measurement as 4-wire transducer • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire one connection • for resistance measurement (2-wire sensor), max. • 2-wire sensor • 2-wire sensor • permissible quiescent current (2-wire sensor), max. • 1.5 mA **Trors/accuracles** **Errors/accuracles** **Errors/accuracles** **Errors/accuracles** **Errors/accuracles** **Desperature error (relative to input range), (+/-) **Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-) **Unitarity error (relative to output range, (+/-) **Linearity error (relative to output range, (+/-) **Linearity error (relative to input range, (+/-) **Output range), (+/-) **Output range, (+/-) **Output range, relative to input range, (+/-) **Output range, relative to input range, (+/-) **Output range, relative to input range, (+/-) **Output relative to output range, (+/-) **Output relative to input range, (+/-) **Output relative to input range, (+/-) **Output limit (operational limit at 25 "C) **Output, relative to input range, (+/-) **Outrent, relative to	Integration and conversion time/resolution per channel	
Settling time • for resistive load • for capacitive load • for capacitive load • for inductive load • for output measurement • for current measurement as 2-wire transducer • for current measurement as 4-wire transducer • for current measurement with two-wire connection • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection • for current four for feature to input range, (+/-) • Resistance, relative to output range, (+/-) • Resistance, relative to input range, (+/-) •	 Resolution with overrange (bit including sign), max. 	12 bit
• for resistive load • for capacitive load • for deductive load • for inductive load • for wollductive load • for wollductive load • for vollductive load • for cournet measurement as 2-wire transducer • for current measurement as 2-wire transducer • for current measurement as 4-wire transducer • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection • for resistance measurement with four-wire connection Connectable encoders • 2-wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracles Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Output ripple (relative to output range), (+/-) Temperature error (relative to output range), (+/-) 1.5 % Temperature error (relative to output range), (+/-) Output ripple (relative to output range), (+/-) Temperature error (relative to output range), (+/-) 1.5 % Temperature error (relative to output range), (+/-) Temperature error (relative to output range), (+/-) 1.5 % Temperature error (relative to output range), (+/-) 1.7 % Perperature error (relative to output range), (+/-) Temperature error (relative to output range), (+/-) 1.8 % Resistance, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input		1 ms
• for capacitive load • for inductive load • for inductive load • for inductive load • for inductive load • for commection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer • for current measurement as 4-wire transducer • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection • for resistance measurement with four-wire connection • Permissible quiescent current (2-wire sensor), max. Errors/accuracles Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Clinearly error (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Clinearly error (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Crosstalk between the outputs, min. 60 dB Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Resistance, relative to output range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Valtage, relative to input range, (+/-) • Valtage, relative to input range, (+/-) • Valtage, relative to input range,	Settling time	
■ for inductive load Encoder Connection of signal encoders ■ for voltage measurement		0.6 ms
Encoder Connection of signal encoders • for voltage measurement as 2-wire transducer • for current measurement as 4-wire transducer • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire on for resistance measurement with four-wire connection • for resistance measurement with four-wire on for permissible quiescent current (2-wire sensor) — permissible quiescent current (2-wire sensor), max. Errors/accuracles Temperature error (relative to input range), (+/-) Crosstalk between the input,s min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Linearity error (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Current, relative to output range, (+/-) • Current, relative to output range, (+/-) • Current, relative to input	for capacitive load	
• for voltage measurement • for current measurement as 2-wire transducer • for current measurement as 4-wire transducer • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection Connectable encoders • 2-wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracies Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Output ripple (relative to output range), et-/-) Temperature error (relative to output range), (+/-) Unearity error (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Output ripple (relative to output range), (+/-) Temperature error (relative to output range), (+/-) Output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to input range, (+/-) • Ourrent, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative	for inductive load	0.5 ms
• for voltage measurement • for current measurement as 2-wire transducer • for current measurement as 4-wire transducer • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection • for resistance measurement with four-wire connection Connectable encoders • 2-wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracies Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. 60 dB Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Uinearity error (relative to output range), (+/-) Crosstalk between the outputs, min. 60 dB Repeat accuracy in steady state at 25 °C (relative to 0.01 %/K Crosstalk between the outputs, min. 60 dB Repeat accuracy in steady state at 25 °C (relative to 0.01 %/K Crosstalk between the outputs, min. 60 dB Repeat accuracy in steady state at 25 °C (relative to 0.01 %/K Crosstalk between the outputs, min. 60 dB Repeat accuracy in steady state at 25 °C (relative to 0.06 % output range), (+/-) 1 % • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to output range, (+/-) • Current, relative to input range, (+	Encoder	
• for current measurement as 2-wire transducer • for current measurement as 4-wire transducer • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection Connectable encoders • 2-wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracies Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Linearity error (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to output range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Output range, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance, r	Connection of signal encoders	
• for current measurement as 4-wire transducer • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection Connectable encoders • 2-wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracies Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Linearity error (relative to output range, bandwidth 0 to 50 kHz), (+/-) Linearity error (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) On1 %/K Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to input range, (+/-) • Resistance,	for voltage measurement	Yes
• for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection • for resistance measurement with four-wire connection Connectable encoders • 2-wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracies Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-) Temperature error (relative to output range), (+/-) 7 Emperature error (relative to output range), (+/-) Temperature error (relative to output range), (+/-) Output ripple (relative to output range), (+/-) Temperature error (relative to output range), (+/-) Output ripple), (+/-) Temperature error (relative to output range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Current, relative to output range, (+/-) • Current, relative to output range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistanc	• for current measurement as 2-wire transducer	Yes; with external supply
connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection Connectable encoders • 2-wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracies Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-) Temperature error (relative to output range), (+/-) Temperature error (relative to output range), (+/-) Output ripple (relative to output range), (+/-) Temperature error (relative to output range), (+/-) Output ripple (relative to output range), (+/-) Output ripple (relative to output range), (+/-) Output ripple (relative to output range), (+/-) Temperature error (relative to output range), (+/-) Output range), (+/-) Output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Current, relative to output range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-	 for current measurement as 4-wire transducer 	Yes
connection • for resistance measurement with four-wire connection Connectable encoders • 2-wire sensor		Yes; Without compensation of the line resistances
Connectable encoders • 2-wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracies Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-) Linearity error (relative to output range), (+/-) Crosstalk between the outputs, min. 60 dB Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) 0.15 % Temperature error (relative to output range), (+/-) Crosstalk between the outputs, min. 60 dB Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) 1 % • Current, relative to output range, (+/-) 1 % • Current, relative to output range, (+/-) 1 % • Current, relative to output range, (+/-) 1 % Basic error limit (operational limit at 25 °C) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-)		No
• 2-wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracies Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-) Linearity error (relative to output range), (+/-) O.15 % Temperature error (relative to output range), (+/-) 0.01 %/K Crosstalk between the outputs, min. 60 dB Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Current, relative to output range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to output range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-)		No
— permissible quiescent current (2-wire sensor), max. Errors/accuracies Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-) Linearity error (relative to output range), (+/-) Temperature error (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Current, relative to output range, (+/-) • Current, relative to output range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-)	Connectable encoders	
Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-) Linearity error (relative to output range), (+/-) Temperature error (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to output range, (+/-) • Current, relative to output range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-)	• 2-wire sensor	Yes
Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-) Linearity error (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Current, relative to output range, (+/-) • Current, relative to output range, (+/-) • Current, relative to output range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-)	, , , , , , , , , , , , , , , , , , , ,	1.5 mA
Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-) Linearity error (relative to output range), (+/-) Temperature error (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Current, relative to output range, (+/-) • Voltage, relative to output range, (+/-) • Current, relative to output range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to output range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-)	Errors/accuracies	
Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-) Linearity error (relative to output range), (+/-) Temperature error (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to output range, (+/-) • Voltage, relative to output range, (+/-) • Current, relative to output range, (+/-) • Voltage, relative to output range, (+/-) • Current, relative to output range, (+/-) • Current, relative to output range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-)	Temperature error (relative to input range), (+/-)	0.006 %/K
Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-) Linearity error (relative to output range), (+/-) Temperature error (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Current, relative to output range, (+/-) • Current, relative to output range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-)		60 dB
Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-) Linearity error (relative to output range), (+/-) Temperature error (relative to output range), (+/-) Temperature error (relative to output range), (+/-) Output range outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Resistance, relative to input range, (+/-)	Repeat accuracy in steady state at 25 °C (relative to input	0.06 %
Linearity error (relative to output range), (+/-) Temperature error (relative to output range), (+/-) Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to output range, (+/-) • Current, relative to output range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Resistance, relative to input range, (+/-)	Output ripple (relative to output range, bandwidth 0 to 50	0.1 %
Crosstalk between the outputs, min. Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to output range, (+/-) • Voltage, relative to output range, (+/-) • Current, relative to output range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Resistance, relative to input range, (+/-)	Linearity error (relative to output range), (+/-)	0.15 %
Repeat accuracy in steady state at 25 °C (relative to output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Current, relative to output range, (+/-) • Current, relative to output range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance, relative to input range, (+/-)	Temperature error (relative to output range), (+/-)	0.01 %/K
output range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Voltage, relative to output range, (+/-) • Current, relative to output range, (+/-) • Sasic error limit (operational limit at 25 °C) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-)	Crosstalk between the outputs, min.	60 dB
 Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) Resistance, relative to input range, (+/-) Voltage, relative to output range, (+/-) Current, relative to output range, (+/-) Basic error limit (operational limit at 25 °C) Voltage, relative to input range, (+/-) Voltage, relative to input range, (+/-) Eurrent, relative to input range, (+/-) Resistance, relative to input range, (+/-) 		0.06 %
 Current, relative to input range, (+/-) Resistance, relative to input range, (+/-) Voltage, relative to output range, (+/-) Current, relative to output range, (+/-) 1 % Current, relative to output range, (+/-) 1 % Sasic error limit (operational limit at 25 °C) Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) Resistance, relative to input range, (+/-) 0.8 %; Linearity error ±0.06 % Resistance, relative to input range, (+/-) 0.8 %; Linearity error ±0.2 % 	Operational error limit in overall temperature range	
 Resistance, relative to input range, (+/-) Voltage, relative to output range, (+/-) Current, relative to output range, (+/-) Basic error limit (operational limit at 25 °C) Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) Resistance, relative to input range, (+/-) Resistance, relative to input range, (+/-) 0.8 %; Linearity error ±0.06 % Resistance, relative to input range, (+/-) 0.8 %; Linearity error ±0.2 % 	 Voltage, relative to input range, (+/-) 	1 %
 Voltage, relative to output range, (+/-) Current, relative to output range, (+/-) Basic error limit (operational limit at 25 °C) Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) Resistance, relative to input range, (+/-) Resistance, relative to input range, (+/-) W Unearity error ±0.06 % Resistance, relative to input range, (+/-) W Unearity error ±0.06 % Unearity error ±0.2 % 	 Current, relative to input range, (+/-) 	1 %
 Current, relative to output range, (+/-) Basic error limit (operational limit at 25 °C) Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) Resistance, relative to input range, (+/-) 0.8 %; Linearity error ±0.06 % Resistance, relative to input range, (+/-) 0.8 %; Linearity error ±0.2 % 	 Resistance, relative to input range, (+/-) 	1 %
Basic error limit (operational limit at 25 °C) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance, relative to input range, (+/-) 0.8 %; Linearity error ±0.06 % 0.8 %; Linearity error ±0.2 %	 Voltage, relative to output range, (+/-) 	1 %
 Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) Resistance, relative to input range, (+/-) 0.8 %; Linearity error ±0.06 % 0.8 %; Linearity error ±0.2 % 	 Current, relative to output range, (+/-) 	1 %
 Current, relative to input range, (+/-) Resistance, relative to input range, (+/-) 0.8 %; Linearity error ±0.06 % 0.8 %; Linearity error ±0.2 % 	Basic error limit (operational limit at 25 °C)	
• Resistance, relative to input range, (+/-) 0.8 %; Linearity error ±0.2 %	Voltage, relative to input range, (+/-)	0.8 %; Linearity error ±0.06 %
	• Current, relative to input range, (+/-)	0.8 %; Linearity error ±0.06 %
Resistance thermometer, relative to input range, (+/- 0.8 %	 Resistance, relative to input range, (+/-) 	0.8 %; Linearity error ±0.2 %
	 Resistance thermometer, relative to input range, (+/-) 	0.8 %
Voltage, relative to output range, (+/-) Output relative to output range, (+/-) Output relative to output range, (+/-) Output relative to output range, (+/-)		
• Current, relative to output range, (+/-) O.8 %		
Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference frequency • Series mode interference (peak value of 30 dB	Series mode interference (peak value of	
interference < rated value of input range), min. ◆ Common mode interference, min. 40 dB		40 dB
Interfaces	Interfaces	
Number of industrial Ethernet interfaces 0	Number of industrial Ethernet interfaces	0
Number of PROFINET interfaces 0	Number of PROFINET interfaces	0
Number of RS 485 interfaces 1; MPI	Number of RS 485 interfaces	1; MPI

Number of DC 422 interferes	
Number of RS 422 interfaces	0
1. Interface	
Interface type	Integrated RS 485 interface
Isolated	No
Interface types	
• RS 485	Yes
Output current of the interface, max.	200 mA
Protocols	
• MPI	Yes
 PROFIBUS DP master 	No
 PROFIBUS DP slave 	No
Point-to-point connection	No
MPI	
 Transmission rate, max. 	187.5 kbit/s
Services	
— PG/OP communication	Yes
— Routing	No
 Global data communication 	Yes
 S7 basic communication 	Yes
— S7 communication	Yes; Only server, configured on one side
 S7 communication, as client 	No; but via CP and loadable FB
— S7 communication, as server	Yes
Communication functions	
PG/OP communication	Yes
Data record routing	No
Global data communication	
• supported	Yes
Number of GD loops, max.	8
Number of GD packets, max.	8
Number of GD packets, fransmitter, max.	8
Number of GD packets, transmitter, max. Number of GD packets, receiver, max.	8
Size of GD packets, max.	22 byte
 Size of GD packets, max. Size of GD packet (of which consistent), max. 	22 byte
S7 basic communication	LL Dylo
supported	Yes
User data per job, max.	
	76 byte 76 byte: 76 bytes (with X_SEND or X_RCV): 64 bytes (with X_RUT or
 User data per job (of which consistent), max. 	76 byte; 76 bytes (with X_SEND or X_RCV); 64 bytes (with X_PUT or X_GET as server)
S7 communication	· ·
• supported	Yes
as server	Yes
as client	Yes; Via CP and loadable FB
User data per job, max.	180 byte; With PUT/GET
 User data per job (of which consistent), max. 	240 byte; as server
S5 compatible communication	
• supported	Yes; via CP and loadable FC
Number of connections	100, the of the foundation of the
• overall	8
usable for PG communication	7
reserved for PG communication	1
adjustable for PG communication, min.	1
	7
— adjustable for PG communication, max.• usable for OP communication	7
— reserved for OP communication	1
adjustable for OP communication, min.	1
— adjustable for OP communication, max.	7
 usable for S7 basic communication 	4
 reserved for S7 basic communication 	0

	٥
 adjustable for S7 basic communication, min. 	0
— adjustable for S7 basic communication, max.	4
S7 message functions	
Number of login stations for message functions, max.	8; Depending on the configured connections for PG/OP and S7 basic communication
Process diagnostic messages	Yes
simultaneously active Alarm-S blocks, max.	300
Test commissioning functions	
Status block	Yes; Up to 2 simultaneously
Single step	Yes
Number of breakpoints	4
Status/control	
 Status/control variable 	Yes
 Variables 	Inputs, outputs, memory bits, DB, times, counters
 Number of variables, max. 	30
of which status variables, max.	30
— of which control variables, max.	14
Forcing	
• Forcing	Yes
Forcing, variables	Inputs, outputs
Number of variables, max.	10
Diagnostic buffer	
• present	Yes
Number of entries, max.	500
•	No
— adjustable	
— of which powerfail-proof	100; Only the last 100 entries are retained
Number of entries readable in RUN, max.	499
— adjustable	Yes; From 10 to 499
— preset	10
Service data	
can be read out	Yes
can be read out Interrupts/diagnostics/status information	Yes
	Yes
Interrupts/diagnostics/status information	Yes
Interrupts/diagnostics/status information Diagnostics indication LED	
Interrupts/diagnostics/status information Diagnostics indication LED • Status indicator digital input (green)	Yes
Interrupts/diagnostics/status information Diagnostics indication LED • Status indicator digital input (green) • Status indicator digital output (green)	Yes
Interrupts/diagnostics/status information Diagnostics indication LED • Status indicator digital input (green) • Status indicator digital output (green) Integrated Functions Frequency measurement	Yes Yes
Interrupts/diagnostics/status information Diagnostics indication LED • Status indicator digital input (green) • Status indicator digital output (green) Integrated Functions Frequency measurement • Number of frequency meters	Yes Yes
Interrupts/diagnostics/status information Diagnostics indication LED • Status indicator digital input (green) • Status indicator digital output (green) Integrated Functions Frequency measurement • Number of frequency meters controlled positioning	Yes Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No
Interrupts/diagnostics/status information Diagnostics indication LED • Status indicator digital input (green) • Status indicator digital output (green) Integrated Functions Frequency measurement • Number of frequency meters	Yes Yes 3; up to 30 kHz (see "Technological Functions" manual)
Interrupts/diagnostics/status information Diagnostics indication LED • Status indicator digital input (green) • Status indicator digital output (green) Integrated Functions Frequency measurement • Number of frequency meters controlled positioning integrated function blocks (closed-loop control)	Yes Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual)
Interrupts/diagnostics/status information Diagnostics indication LED • Status indicator digital input (green) • Status indicator digital output (green) Integrated Functions Frequency measurement • Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller	Yes Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions"
Interrupts/diagnostics/status information Diagnostics indication LED • Status indicator digital input (green) • Status indicator digital output (green) Integrated Functions Frequency measurement • Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller Number of pulse outputs Limit frequency (pulse)	Yes Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual)
Interrupts/diagnostics/status information Diagnostics indication LED • Status indicator digital input (green) • Status indicator digital output (green) Integrated Functions Frequency measurement • Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller Number of pulse outputs Limit frequency (pulse) Potential separation	Yes Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual)
Interrupts/diagnostics/status information Diagnostics indication LED Status indicator digital input (green) Status indicator digital output (green) Integrated Functions Frequency measurement Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs	Yes Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual) 2.5 kHz
Interrupts/diagnostics/status information Diagnostics indication LED Status indicator digital input (green) Status indicator digital output (green) Integrated Functions Frequency measurement Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs Potential separation digital inputs	Yes Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual) 2.5 kHz
Interrupts/diagnostics/status information Diagnostics indication LED Status indicator digital input (green) Status indicator digital output (green) Integrated Functions Frequency measurement Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs Potential separation digital inputs between the channels	Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual) 2.5 kHz Yes No
Interrupts/diagnostics/status information Diagnostics indication LED Status indicator digital input (green) Status indicator digital output (green) Integrated Functions Frequency measurement Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs Potential separation digital inputs between the channels between the channels and backplane bus	Yes Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual) 2.5 kHz
Interrupts/diagnostics/status information Diagnostics indication LED Status indicator digital input (green) Status indicator digital output (green) Integrated Functions Frequency measurement Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs Potential separation digital inputs between the channels between the channels and backplane bus	Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual) 2.5 kHz Yes No Yes
Interrupts/diagnostics/status information Diagnostics indication LED Status indicator digital input (green) Status indicator digital output (green) Integrated Functions Frequency measurement Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs Potential separation digital inputs between the channels between the channels and backplane bus Potential separation digital outputs Potential separation digital outputs Potential separation digital outputs	Yes Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual) 2.5 kHz Yes No Yes Yes
Interrupts/diagnostics/status information Diagnostics indication LED Status indicator digital input (green) Status indicator digital output (green) Integrated Functions Frequency measurement Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs Potential separation digital inputs between the channels between the channels and backplane bus Potential separation digital outputs Potential separation digital outputs Potential separation digital outputs Potential separation digital outputs Potential separation digital outputs Potential separation digital outputs Potential separation digital outputs	Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual) 2.5 kHz Yes No Yes Yes Yes
Interrupts/diagnostics/status information Diagnostics indication LED Status indicator digital input (green) Status indicator digital output (green) Integrated Functions Frequency measurement Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs Potential separation digital inputs between the channels between the channels and backplane bus Potential separation digital outputs Potential separation digital outputs Potential separation digital outputs between the channels between the channels between the channels between the channels, in groups of	Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual) 2.5 kHz Yes No Yes Yes No Yes 8
Interrupts/diagnostics/status information Diagnostics indication LED Status indicator digital input (green) Status indicator digital output (green) Integrated Functions Frequency measurement Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs Potential separation digital inputs between the channels between the channels and backplane bus Potential separation digital outputs	Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual) 2.5 kHz Yes No Yes Yes Yes
Interrupts/diagnostics/status information Diagnostics indication LED Status indicator digital input (green) Status indicator digital output (green) Integrated Functions Frequency measurement Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs Potential separation digital inputs between the channels between the channels and backplane bus Potential separation digital outputs Potential separation digital outputs between the channels and backplane bus Potential separation analog inputs	Yes Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual) 2.5 kHz Yes No Yes Yes No Yes Yes Yes 8 Yes
Interrupts/diagnostics/status information Diagnostics indication LED Status indicator digital input (green) Status indicator digital output (green) Integrated Functions Frequency measurement Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs Potential separation digital inputs between the channels between the channels and backplane bus Potential separation digital outputs Potential separation digital outputs between the channels and backplane bus Potential separation analog inputs Potential separation analog inputs Potential separation analog inputs	Yes Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual) 2.5 kHz Yes No Yes
Interrupts/diagnostics/status information Diagnostics indication LED Status indicator digital input (green) Status indicator digital output (green) Integrated Functions Frequency measurement Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs Potential separation digital inputs between the channels between the channels and backplane bus Potential separation digital outputs Potential separation digital outputs between the channels between the channels between the channels between the channels and backplane bus Potential separation analog inputs Potential separation analog inputs Potential separation analog inputs Potential separation analog inputs Potential separation analog inputs Potential separation analog inputs	Yes Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual) 2.5 kHz Yes No Yes
Interrupts/diagnostics/status information Diagnostics indication LED Status indicator digital input (green) Status indicator digital output (green) Integrated Functions Frequency measurement Number of frequency meters controlled positioning integrated function blocks (closed-loop control) PID controller Number of pulse outputs Limit frequency (pulse) Potential separation Potential separation digital inputs Potential separation digital inputs between the channels between the channels and backplane bus Potential separation digital outputs Potential separation digital outputs between the channels and backplane bus Potential separation analog inputs Potential separation analog inputs Potential separation analog inputs	Yes Yes Yes 3; up to 30 kHz (see "Technological Functions" manual) No Yes; PID controller (see "Technological Functions" manual) Yes 3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual) 2.5 kHz Yes No Yes

Potential separation analog outputs	
 Potential separation analog outputs 	Yes; common for analog I/O
 between the channels 	No
 between the channels and backplane bus 	Yes
Isolation	
Isolation tested with	600 V DC
Ambient conditions	
Ambient temperature during operation	
• min.	0°C
• max.	60 °C
Configuration	
Configuration software	
• STEP 7	Yes; STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with HSP 203
STEP 7 Lite	No
Programming	
 Command set 	see instruction list
 Nesting levels 	8
 System functions (SFC) 	see instruction list
 System function blocks (SFB) 	see instruction list
Programming language	
— LAD	Yes
— FBD	Yes
— STL	Yes
— SCL	Yes
— CFC	Yes
— GRAPH	Yes
— HiGraph®	Yes
Know-how protection	
 User program protection/password protection 	Yes
 Block encryption 	Yes; With S7 block Privacy
Dimensions	
Width	120 mm
Height	125 mm
Depth	130 mm
Weights	
Weight, approx.	660 g
last modified:	3/25/2021 🗗